Disclaimer. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



booted head for pushbutton - XAC-A - lower, slow-fast

Local distributor code:

393522758

XACA924

EAN Code: 3389110740158

Main

Range of product	Harmony XAC
Product or component type	Head for push-button
Component name	XACA
Marking	Lower, slow-fast
Operator additional information	Booted
Product compatibility	XACA217.

Complementary

Net weight 0.01 kg

Environment

Standards	IEC 60204-32 CSA C22.2 No 14 IEC 60947-5-1 IEC 60947-5-1 IEC 60204-32 UL 508	
Ambient air temperature for operation	-2570 °C	
Ambient air temperature for storage	-4070 °C	
Vibration resistance	15 gn (f= 10500 Hz) conforming to IEC 60068-2-6	
Shock resistance	100 gn conforming to IEC 60068-2-27	
Electrical shock protection class	Class II conforming to IEC 61140	
IP degree of protection	IP65 conforming to IEC 60529	
IK degree of protection	IK08 conforming to IEC 62262	

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	2.0 cm
Package 1 Width	3.5 cm
Package 1 Length	5.0 cm
Package 1 Weight	10.0 g
Unit Type of Package 2	S01
Number of Units in Package 2	50

Package 2 Height	15.0 cm	
Package 2 Width	15.0 cm	
Package 2 Length	40.0 cm	
Package 2 Weight	697.0 a	

Logistical informations

Country of origin FR

Contractual warranty

Warranty 18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

☑ Environmental footprint	
Environmental Disclosure	Product Environmental Profile

Use Better

⊗ Materials and Substances	
Packaging without single use plastic	No
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
REACh Regulation	REACh Declaration

Use Again

○ Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No