# Eaton 026642

# Catalog Number: 026642

Eaton Moeller® series STI Control transformer, 1 kVA, Rated input voltage 230± 5 % V, Rated output voltage 230 V

# General specifications

#### **Product Name**

Eaton Moeller® series STI Control transformer

# Product Length/Depth

150 mm

# Product Width

151 mm

# Certifications

CSA-C22.2 No. 66

IEC/EN 60204-1, ÖVE-EN 13

UL 5085-2

UL report applies to both US and

Canada

VDE 0570 Part 2-6 (safety

transformers)

UL Recognized VDE 0570 Part 2-4 (isolating

transformer)

UL 506

CE

IEC/EN 61558-2-2

UL File No.: E167225 CSA-C22.2 No. 66.2-06 IEC/EN 61558-2-2/2-4/2-6

UL5085-1

VDE 0113, VDE 0100 Part 410

VDE 0570 Part 2-2

DE 0570 Part 2-2

# Catalog Number

026642

#### EAN

4015080266426

#### **Product Height**

145 mm

# **Product Weight**

13.289 kg

# **Catalog Notes**

Electrical characteristics: all details for no-load loss, short-circuit loss (copper losses), short-circuit voltage and efficiency values relate to a temperature







# Features & Functions

#### **Features**

Fully Vacuum-impregnated

Separate windings

Reinforced insulation

# General

Ambient operating temperature - min

-25 °C

Ambient operating temperature - max

40 °C

Connection lug

Yes for > 115 A

Connection type

Terminations, < 115 A

**Duty factor** 

100 %

Insulation class

В

Primary tapping

±5%

**Product category** 

Single-phase control transformers ST

Suitable for

Branch circuits, (UL/CSA)

Type

Single-phase control, isolating and safety transformer

# Electrical rating

### Efficiency

95 %

No-load losses

27 W

Rated frequency - min

50 Hz

Rated frequency - max

60 Hz

Rated power

1 VA

Relative short-circuit voltage

2.9 %

# Design verification

Equipment heat dissipation, current-dependent Pvid

0 W

Heat dissipation capacity Pdiss

0 W

Heat dissipation per pole, current-dependent Pvid

W C

Rated operational current for specified heat dissipation (In)

0 A

Static heat dissipation, non-current-dependent Pvs

56 W

10.2.2 Corrosion resistance

Meets the product standard's requirements.

#### Short-circuit losses

29 W

#### Short-time rating

2.8 kVA

#### Voltage rating - max

600 V

#### 10.2.3.1 Verification of thermal stability of enclosures

Meets the product standard's requirements.

# 10.2.3.2 Verification of resistance of insulating materials to normal heat

Meets the product standard's requirements.

# 10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects

Meets the product standard's requirements.

# 10.2.4 Resistance to ultra-violet (UV) radiation

Meets the product standard's requirements.

#### 10.2.5 Lifting

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.2.6 Mechanical impact

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.2.7 Inscriptions

Meets the product standard's requirements.

# 10.3 Degree of protection of assemblies

Does not apply, since the entire switchgear needs to be evaluated.

# 10.4 Clearances and creepage distances

Meets the product standard's requirements.

# 10.5 Protection against electric shock

Does not apply, since the entire switchgear needs to be evaluated.

# 10.6 Incorporation of switching devices and components

Does not apply, since the entire switchgear needs to be evaluated.

# 10.7 Internal electrical circuits and connections

Is the panel builder's responsibility.

### 10.8 Connections for external conductors

Is the panel builder's responsibility.

#### 10.9.2 Power-frequency electric strength

Is the panel builder's responsibility.

# 10.9.3 Impulse withstand voltage

Is the panel builder's responsibility.

#### 10.9.4 Testing of enclosures made of insulating material

Is the panel builder's responsibility.

# 10.10 Temperature rise

The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

#### 10.11 Short-circuit rating

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

#### 10.12 Electromagnetic compatibility

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

#### 10.13 Mechanical function

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

# Resources

#### Application notes

eaton-transformer-stz-sti-stn-dtz-uti-ap009002-en-us.pdf

#### **Brochures**

eaton-transformers-brochure-br009002en-en-us.pdf

#### Catalogs

eaton-product-overview-for-machinery-catalogue-ca 08103003 zen-enus.pdf

#### Declarations of conformity

DA-DC-00004447.pdf

DA-DC-00004421.pdf

#### **Drawings**

eaton-general-transformer-sti-control-transformer-dimensions-017.eps

#### eCAD model

ETN.026642.edz

#### mCAD model

DA-CD-sti1\_0\_230

DA-CS-sti1\_0\_230

# System overview

eaton-general-diagram-sti-control-transformer-explosion-drawing.eps



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

© 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark.

All other trademarks are property of their respective owners.



Eaton.com/socialmedia