

INFORMATION/DATA SHEET
Aurora Charger Multi Adaptor RS7015958
Guardian Charger Multi Adaptor RS7015951

Universal mains charger for the above Portable Floodlights. Fully automatic 3 stage electronic charger providing advanced monitoring and control and fast recharging.

This charger is supplied with adaptors for UK (standard 3 pin); Europe (2pin); US (2pin) AUS (2 pin).

To change adaptor plugs first remove the fitted adaptor (usually UK 3 pin)

The adaptors are intentionally a tight fit and should be removed and re-fitted carefully. They will only fit one way.

To remove it is suggested you hold charger with both hands with the plug adaptor facing you at the 12 o'clock position (upward). Use both thumbs to firmly and carefully push the adaptor upwards. It will slide out of the charger. Select the required adaptor plug and fit to the charger. Ensure the plug is slid securely into place. It should fit exactly and will require firm pressure.

3 stage indication of the charging state is provided by a multi-function LED

Yellow = Normal charging.

Green = Maintenance/Standby charge (Battery fully charged)

A red light indicates a fault condition.

If required this charger is suitable for permanent connection to the Floodlight. The green LED will remain illuminated and the battery will be maintained at full capacity. In this mode the charger requires negligible electrical power.

Specifications:-

Switch-mode fully electronic 3 stage charger

Input – 100-240 vac: 50/60 Hz: 500ma/50va

Output – 12-15 vdc: 2.0A; 24va

Fuse – Internal 2A (non-replaceable)

Isolation – Class 2. Medical grade. No ground required.

Environmental – Indoor use only: 0°C to 40°C.

Charging time – 6-8 hours (from full discharged)

Charge control – fully automatic; suitable for continuous charging.