

## **ENERGY AND AUTOMATION**

Order code	Rated current le	Auxiliary supply voltage	Qty per pkg	Wt
	[A]	[V]	n°	[kg]


Single and three-phase systems.

Maximum AC current and minimum cosφ. Delayed trip.

Phase loss and incorrect phase sequence. Instantaneous trip. Auxiliary AC power supply.

Automatic or manual reset.

PMA50 A240	5 or 16A	220-240VAC	1	0.251
PMA50 A415		380-415VAC	1	0.251
PMA50 A480		440-480VAC	1	0.251



## **General characteristics**

- Pump protection relay against dry running, auxiliary AC power supply
- Motor under-load and over-current control
- Direct connection up to 16A max or by current transformer (CT)
- **Excellent tripping accuracy**
- Voltage control range 80-660VAC
- Current control range 0.1-16A
- Resetting and enabling consent input
- 1 relay output relay with 1 changeover contact (SPDT)
- Modular DIN 43880 housing, 3 module
- IEC protection degree: IP40 on front (only when placed in IP40 enclosure or control board); IP20 at terminals.

## **ADJUSTMENTS**

"Cos

min" Minimum cosφ threshold 0.1-0.99

(under-load/dry running)

"Imax" Maximum (over) current threshold

10-100%le

"Trip delay" Tripping time for minimum cos\(\phi\) and

maximum current 0.1-10s

"Inhibition time" Tripping delay for external input or at

power up 1-60s

"Aut. reset delay"

"Mode"


Automatic reset time OFF-100min


Rated current 5A or 16A


Single or three phase


External reset On or Off.


Certifications and compliance
Certifications obtained: EAC; UL Listed, for USA and
Canada (CULus - File £93601), as Auxiliary Devices Modular ampere monitoring relays.
Compliant with standards: IEC/EN 60255-5,
IEC/EN 61000-6-2, IEC/EN 61000-6-3, UL 508,
CSA G22.2 n° 14.

















16A

1 phase 3 phase











## **ENERGY AND AUTOMATION**

CIRCUIT  current  φ	Single and three-phase pump pi (motor under-load and over-curre monitoring for max AC current, r phase loss and incorrect phase s 5 or 16A  5 or 16A  10-100le  0.1-0.99 cos\(\phi\) (MIN)  0.1-10s  1-60s  OFF-100min	ent control) min cosφ, sequence  50/60H  5le fo 160A fo	or 1s or 10ms on 10ms ant 16A rent transformer  16A — 0.1-0.99 cosφ (MIN and MAX) 0.1-30s		
current φ	(motor under-load and over-curre monitoring for max AC current, r phase loss and incorrect phase s  5 or 16A  5 or 16A  10-100le  0.1-0.99 cosφ (MIN)  0.1-10s  1-60s  OFF-100min	ent control) min cosφ, sequence  50/60H  5le fo 160A fo Consta	for minimum and maximum cosφ monitoring  16A  Hz ±5%  or 1s or 10ms ant 16A rent transformer  16A — 0.1-0.99 cosφ (MIN and MAX) 0.1-30s		
current φ	5 or 16A 10-100le 0.1-0.99 cosφ (MIN) 0.1-10s 1-60s 0FF-100min	5le fo 160A fo Consta	1z ±5%  or 1s  or 10ms  ant 16A  rent transformer  16A  —  0.1-0.99 cosφ (MIN and MAX)  0.1-30s		
φ	5 or 16A 10-100le 0.1-0.99 cosφ (MIN) 0.1-10s 1-60s 0FF-100min	5le fo 160A fo Consta	1z ±5%  or 1s  or 10ms  ant 16A  rent transformer  16A  —  0.1-0.99 cosφ (MIN and MAX)  0.1-30s		
φ	10-100le 0.1-0.99 cosφ (MIN) 0.1-10s 1-60s OFF-100min	5le fo 160A fo Consta	or 1s or 10ms on 10ms ant 16A rent transformer  16A — 0.1-0.99 cosφ (MIN and MAX) 0.1-30s		
φ	10-100le 0.1-0.99 cosφ (MIN) 0.1-10s 1-60s OFF-100min	160A fo Consta	or 10ms ant 16A rent transformer  16A — 0.1-0.99 cosφ (MIN and MAX) 0.1-30s		
φ	10-100le 0.1-0.99 cosφ (MIN) 0.1-10s 1-60s OFF-100min	Consta	nnt 16A rent transformer  16A — 0.1-0.99 cosφ (MIN and MAX) 0.1-30s		
φ	10-100le 0.1-0.99 cosφ (MIN) 0.1-10s 1-60s OFF-100min		16A — 0.1-0.99 cos\(\phi\) (MIN and MAX) 0.1-30s		
φ	10-100le 0.1-0.99 cosφ (MIN) 0.1-10s 1-60s OFF-100min	Direct or by curi	16A — 0.1-0.99 cosφ (MIN and MAX) 0.1-30s		
φ	10-100le 0.1-0.99 cosφ (MIN) 0.1-10s 1-60s OFF-100min		— 0.1-0.99 cosφ (MIN and MAX) 0.1-30s		
φ	0.1-0.99 cosφ (MIN) 0.1-10s 1-60s OFF-100min		0.1-30s		
	0.1-10s 1-60s 0FF-100min		0.1-30s		
ting	1-60s OFF-100min				
ting	OFF-100min				
ting			1-60s		
	0	OFF-100min —			
	Consent for running/resetting —				
		±1% with const	ant parameters		
		8066	50VAC		
		601	ms		
		220-24	40VAC		
	3	80-415VAC (maximu	m voltage for UL/CSA)		
		440-48			
	0.85-1.1 Us		0.85-1.1 Us		
	50/60Hz ±5%		50/60Hz ±5%		
	4.5VA		4.4VA		
	2.3W		2.4W		
'					
	1		2		
	Normally energised, de-energises at tripping	1	Normally energised / de-energised (ON-OFF) (configurable)		
	1 changeover contact SPDT each				
	250VAC				
	400VAC				
current Ith	8A				
lesignation	B300				
	10 <sup>5</sup> cycles				
	30x10 <sup>6</sup> cycles				
	1 green LED for power on/inhibition 2 red LEDs for minimum/maximum tripping				
I					
		0.8Nm (7lbin: 7-9	Olbin per UL/CSA)		
	0.2-4.0mm² (24-12AWG; 18-12 AWG per UL/CSA)				
I	U.E	(2.112.000)			
		600	VAC		
age Uimp	6kV				
	2.5kV				
Jilago		2.0			
		_20	±60°C		
		-30	TOU U		
		Colf outinguish	ning nalvamida		
	ge Uimp Iltage	ge Uimp	1 green LED for pr 2 red LEDs for minimum 0.8Nm (7lbin; 7-9 0.2-4.0mm² (24-12AWG; 600° ge Uimp		