



---

## Contents

<b>1</b>	<b>Getting started</b> .....	<b>5</b>
1.1	Powering up STEVAL-IDB007V1 evaluation board running the sensor profile firmware (peripheral role).....	5
1.2	Install the BlueNRG app for smartphones (central role).....	6
1.3	Run BlueNRG app for smartphones.....	6
<b>2</b>	<b>SW demonstration applications</b> .....	<b>8</b>
<b>3</b>	<b>References</b> .....	<b>9</b>
<b>4</b>	<b>List of acronyms</b> .....	<b>10</b>
<b>5</b>	<b>Revision history</b> .....	<b>11</b>

## List of tables

Table 1: Reference information .....	9
Table 2: List of acronyms used in the document .....	10
Table 3: Document revision history .....	11

---

## List of figures

Figure 1: STEVAL-IDB007V1 Bluetooth® low energy evaluation board .....	1
Figure 2: STEVAL-IDB007V1 power options.....	6
Figure 3: Smartphone BlueNRG SensorApp acceleration notification .....	7
Figure 4: Smartphone BlueNRG SensorApp RSSI notifications .....	7

# 1 Getting started

The evaluation board is preprogrammed with sensor profile firmware (BLE\_SensorDemo.hex) which allows to set and establish a connection with a smartphone (iOS or Android) running a BlueNRG sensor application which works with the sensor profile firmware running on the STEVAL-IDB007V1 evaluation board.

The sensor profile firmware implements a proprietary Bluetooth profile which exposes two services: acceleration and environmental service.

The acceleration service contains the following characteristics:

- **Acceleration:** it gives the current value of the acceleration detected by the MEMS sensor on the STEVAL-IDB007V1 board.
- **Free fall characteristic:** it allows detection of free-fall condition by the LSM6DS3 MEMS sensor on the STEVAL-IDB007V1 board (the condition is detected if the acceleration on the 3 axes is near zero for a certain amount of time).

The environmental service contains characteristics that expose data from some environmental sensors, such as temperature sensors.


## 1.1 Powering up STEVAL-IDB007V1 evaluation board running the sensor profile firmware (peripheral role)

Two power options are available:

- **Batteries** - To power the STEVAL-IDB007V1 evaluation board using batteries, 2 AAA batteries must be inserted into the battery holder at the rear of the board, and jumper JP1 set to position 2-3 and jumper JP2 set to position 1-2 ([Figure 2: "STEVAL-IDB007V1 power options"](#)).
- **USB** - To power the STEVAL-IDB007V1 evaluation board through USB, jumper JP1 must be in position 1-2 and jumper JP2 set to position 2-3 ([Figure 2: "STEVAL-IDB007V1 power options"](#)). Connect a USB cable to the micro-USB connector ([Figure 2: "STEVAL-IDB007V1 power options"](#)) and to a PC USB port.

Once powered, the STEVAL-IDB007V1 sensor profile firmware starts advertising, waiting for a smartphone to connect to it.

Figure 2: STEVAL-IDB007V1 power options



## 1.2 Install the BlueNRG app for smartphones (central role)

- Two versions (Android and iOS) of the smartphone sensor application are available for download on the specific web pages ([Table 1: "Reference information"Android & iOS SensorApp](#)).
- Install the smartphone SensorApp application on the selected smartphone.

## 1.3 Run BlueNRG app for smartphones


- Launch the BlueNRG SensorApp application on the smartphone
- It starts scanning for the BlueNRG sensor peripheral. A device called "BlueNRG" appears on the screen (this is the STEVAL-IDB007V1 running the sensor profile firmware)
- Tap on the BlueNRG name to connect to the STEVAL-IDB007V1 running the sensor profile firmware. The BlueNRG SensorApp application enables notifications on the acceleration characteristic and displays the received value on the screen.

Figure 3: Smartphone BlueNRG SensorApp acceleration notification



- Data from environmental sensors are also periodically read and displayed.

Figure 4: Smartphone BlueNRG SensorApp RSSI notifications



## 2 SW demonstration applications

- In order to develop a software application for the STEVAL-IDB007V1 evaluation board, it is recommended to start with the reference demonstration applications provided within the BlueNRG-1 DK software package (STSW-BLUENRG1-DK) available on the STEVAL-IDB007V1 web page.
- Unzip the file, launch the related installer and follow installation steps (the default installation path is C:\Program Files (x86)\STMicroelectronics\BlueNRG-1 DK x.x.x)
- Wait for the package installation to complete.
- The Projects folder in BlueNRG-1 DK SW package contains the available BlueNRG-1 demonstration applications, IAR projects, sources and header files.
- IAR Embedded Workbench for ARM (EWARM) tool is needed for building and downloading software applications running on the BlueNRG-1 microcontroller.



For a description of the available BlueNRG-1 demonstration applications and supported platforms, refer to BlueNRG-1 development kits user manual available on the related web page. The BLE\_SensorDemo.hex prebuilt binary image is also provided within the BlueNRG-1 DK software package, in the Firmware folder.

Keil MDK-ARM and Atollic TrueStudio for ARM (GCC) toolchains projects are also available.

### 3 References

**Table 1: Reference information**

What	Where	Description
BlueNRG-1 Bluetooth Low Energy wireless System on Chip	<a href="http://www.st.com/bluenrg-1">www.st.com/bluenrg-1</a>	BlueNRG-1 device web page
Bluetooth Low Energy Specification	<a href="https://www.bluetooth.org/en-us/specification/adopted-specifications">https://www.bluetooth.org/en-us/specification/adopted-specifications</a>	Bluetooth Low Energy specification web page
Smartphone Android 4.3 Sensor App	<a href="https://play.google.com/store/apps/details?id=com.st.blunrg">https://play.google.com/store/apps/details?id=com.st.blunrg</a>	Android 4.3 BlueNRG Sensor App web page
Smartphone iOS Sensor App	<a href="https://itunes.apple.com/us/app/bluenrg/id705873549?l=it&amp;ls=1&amp;mt=8">https://itunes.apple.com/us/app/bluenrg/id705873549?l=it&amp;ls=1&amp;mt=8</a>	iOS BlueNRG Sensor App web page
STSW-BLUENRG1-DK	STEVAL-IDB007V1 web page, Tools and Software section	BlueNRG-1 DK SW package with reference demonstration applications
STEVAL-IDB007V1	<a href="http://www.st.com/bluenrg-1">www.st.com/bluenrg-1</a> , Evaluation Tools section	STEVAL-IDB007V1 platform web page

## 4 List of acronyms

Table 2: List of acronyms used in the document

Term	Meaning
BLE	Bluetooth Low Energy
DK	Development kit
SW	Software
USB	Universal serial bus

## 5 Revision history

Table 3: Document revision history

Date	Revision	Changes
14-Jul-2016	1	Initial release.

**IMPORTANT NOTICE – PLEASE READ CAREFULLY**

STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice. Purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST's terms and conditions of sale in place at the time of order acknowledgement.

Purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of Purchasers' products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

ST and the ST logo are trademarks of ST. All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2016 STMicroelectronics – All rights reserved