Product data sheet Characteristics

K50D002UP

Cam changeover switch, Harmony K, front mounting, plastic, 2 poles, position 0, 30 degree, 50A, 64x64mm, marked 1/0/2

Range of product	Harmony K		
Product or component type	Complete cam switch		
Component name	K50		
[lth] conventional free air thermal current	50 A		
Mounting location	Front		
Fixing mode	4 holes		
Cam switch head type	With front plate 64 x 64 mm		
Type of operator	Black handle		
Rotary handle padlocking	Without		
Presentation of legend	With metallic legend, 1 - 0 - 2 black marking		
Cam switch function	Changeover switch		
Return	Without		
Off position	With Off position		
Poles description	2P		
Switching positions	Left: 0° - 300° Right: 0° - 60°		
IP degree of protection	IP40 conforming to IEC 60529		

Complementary

Switching angle	60 °	
[Ui] rated insulation voltage	690 V (pollution degree 3) conforming to IEC 60947-1	
Short-circuit current	5000 A	
Short-circuit protection	63 A cartridge fuse, type gG	
[Uimp] rated impulse withstand voltage	6 KV conforming to EN 947-1 6 kV conforming to IEC 947-1	
Contact operation	Slow-break	
Positive opening	With	
Electrical connection	Captive screw clamp terminals flexible, clamping capacity: 2 x 6 mm ² Captive screw clamp terminals solid, clamping capacity: 2 x 10 mm ²	
Tightening torque	2 N.m	

Switching capacity in mA 15000 mA DC at 120 V 2 contact(s) for inductive letation in the contact of the contac	
15000 mA DC at 60 V 1 contact(s) for inductive locations and DC at 140 V 3 contact(s) for inductive locations and DC at 140 V 3 contact(s) for inductive locations and DC at 48 V 1 contact(s) for inductive locations and DC at 48 V 1 contact(s) for inductive locations and DC at 30 V 1 contact(s) for inductive locations and DC at 30 V 1 contact(s) for inductive locations and DC at 60 V 2 contact(s) for inductive locations and DC at 90 V 3 contact(s) for inductive locations and DC at 110 V 1 contact(s) for inductive locations and DC at 220 V 2 contact(s) for inductive locations and DC at 220 V 2 contact(s) for inductive locations and DC at 120 V 2 contact(s) for resistive locations and DC at 120 V 2 contact(s) for resistive locations and DC at 180 V 3 contact(s) for resistive locations and DC at 180 V 3 contact(s) for resistive locations and DC at 180 V 3 contact(s) for resistive locations and DC at 180 V 3 contact(s) for resistive locations and DC at 24 V 1 contact(s) for resistive locations and DC at 48 V 1 contact(s) for inductive locations and DC at 48 V 2 contact(s) for inductive locations and DC at 48 V 2 contact(s) for inductive locations and DC at 48 V 2 contact(s) for resistive locations and DC at 48 V 2 contact(s) for resistive locations and DC at 48 V 2 contact(s) for resistive locations and DC at 48 V 2 contact(s) for resistive locations and DC at 48 V 2 contact(s) for resistive locations and DC at 48 V 2 contact(s) for resistive locations and DC at 48 V 2 contact(s) for resistive locations and DC at 48 V 2 contact(s) for resistive locations and DC at 70 V 3 contact(s) for resistive locations and DC at 70 V 3 contact(s) for resistive locations and DC at 70 V 3 contact(s) for resistive locations and DC at 70 V 3 contact(s) for resistive locations and DC at 70 V 3 contact(s) for resistive locations and DC at 70 V 3 contact(s) for resistive locations and DC at 70 V 3 contact(s) for resistive locations and DC at 70 V 3 contact(s) for resistive locations and DC at 70 V 3 contact(s) for resistive locatic for	,
20000 mA DC at 140 V 3 contact(s) for inductive lo 20000 mA DC at 48 V 1 contact(s) for inductive lo 20000 mA DC at 48 V 1 contact(s) for inductive lo 30000 mA DC at 95 V 2 contact(s) for inductive lo 30000 mA DC at 30 V 1 contact(s) for inductive lo 30000 mA DC at 60 V 2 contact(s) for inductive lo 30000 mA DC at 90 V 3 contact(s) for inductive lo 3500 mA DC at 110 V 1 contact(s) for inductive lo 3500 mA DC at 120 V 2 contact(s) for inductive lo 3500 mA DC at 330 V 3 contact(s) for inductive lo 37000 mA DC at 330 V 3 contact(s) for resistive lo 37000 mA DC at 180 V 3 contact(s) for resistive lo 37000 mA DC at 180 V 3 contact(s) for resistive lo 40000 mA DC at 48 V 1 contact(s) for resistive lo 40000 mA DC at 48 V 1 contact(s) for inductive lo 40000 mA DC at 48 V 2 contact(s) for inductive lo 40000 mA DC at 48 V 2 contact(s) for inductive lo 40000 mA DC at 50 V 1 contact(s) for inductive lo 40000 mA DC at 50 V 2 contact(s) for inductive lo 40000 mA DC at 50 V 2 contact(s) for inductive lo 40000 mA DC at 50 V 3 contact(s) for resistive lo 50000 mA DC at 24 V 1 contact(s) for resistive lo 50000 mA DC at 24 V 1 contact(s) for resistive lo 50000 mA DC at 24 V 1 contact(s) for resistive lo 50000 mA DC at 48 V 2 contact(s) for resistive lo 50000 mA DC at 70 V 3 contact(s) for resistive lo 50000 mA DC at 70 V 3 contact(s) for resistive lo 50000 mA DC at 70 V 3 contact(s) for resistive lo 50000 mA DC at 70 V 3 contact(s) for resistive lo 50000 mA DC at 70 V 3 contact(s) for resistive lo 50000 mA DC at 70 V 3 contact(s) for resistive lo 50000 mA DC at 70 V 3 contact(s) for resistive lo 50000 mA DC at 70 V 3 contact(s) for resistive lo 50000 mA DC at 70 V 3 contact(s) for resistive lo 50000 mA DC at 70 V 3 contact(s) for resistive lo 50000 mA DC at 70 V 3 contact(s) for resistive lo 50000 mA DC at 70 V 3 contact(s) for resistive lo 50000 mA DC at 70 V 3 contact(s) for resistive lo 50000 mA DC at 70 V 3 contact(s) for resistive lo 50000 mA DC at 70 V 3 contact(s) for resistive lo 50000 mA DC at 70 V 3 contact(s) for resis	,
20000 mA DC at 48 V 1 contact(s) for inductive los 20000 mA DC at 95 V 2 contact(s) for inductive los 30000 mA DC at 30 V 1 contact(s) for inductive los 30000 mA DC at 30 V 1 contact(s) for inductive los 30000 mA DC at 90 V 3 contact(s) for inductive los 3500 mA DC at 110 V 1 contact(s) for inductive los 3500 mA DC at 220 V 2 contact(s) for inductive los 3500 mA DC at 330 V 3 contact(s) for inductive los 3500 mA DC at 330 V 3 contact(s) for resistive los 37000 mA DC at 120 V 2 contact(s) for resistive los 37000 mA DC at 180 V 3 contact(s) for resistive los 37000 mA DC at 180 V 3 contact(s) for resistive los 40000 mA DC at 140 V 3 contact(s) for resistive los 40000 mA DC at 24 V 1 contact(s) for resistive los 40000 mA DC at 48 V 1 contact(s) for inductive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 70 V 3 contact(s) for resistive los 50000 mA DC at 24 V 1 contact(s) for resistive los 50000 mA DC at 48 V 2 contact(s) for resistive los 50000 mA DC at 48 V 2 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 50	,
20000 mA DC at 95 V 2 contact(s) for inductive los 30000 mA DC at 30 V 1 contact(s) for inductive los 30000 mA DC at 60 V 2 contact(s) for inductive los 30000 mA DC at 90 V 3 contact(s) for inductive los 3500 mA DC at 110 V 1 contact(s) for inductive los 3500 mA DC at 220 V 2 contact(s) for inductive los 3500 mA DC at 220 V 2 contact(s) for inductive los 3500 mA DC at 330 V 3 contact(s) for inductive los 37000 mA DC at 120 V 2 contact(s) for resistive los 37000 mA DC at 180 V 3 contact(s) for resistive los 37000 mA DC at 180 V 3 contact(s) for resistive los 40000 mA DC at 60 V 1 contact(s) for resistive los 40000 mA DC at 48 V 1 contact(s) for inductive los 40000 mA DC at 48 V 1 contact(s) for inductive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 95 V 2 contact(s) for inductive los 40000 mA DC at 95 V 2 contact(s) for resistive los 50000 mA DC at 48 V 1 contact(s) for resistive los 50000 mA DC at 48 V 2 contact(s) for resistive los 50000 mA DC at 48 V 2 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 500	
30000 mA DC at 30 V 1 contact(s) for inductive los 30000 mA DC at 60 V 2 contact(s) for inductive los 30000 mA DC at 90 V 3 contact(s) for inductive los 3500 mA DC at 110 V 1 contact(s) for inductive los 3500 mA DC at 220 V 2 contact(s) for inductive los 3500 mA DC at 330 V 3 contact(s) for inductive los 3500 mA DC at 330 V 3 contact(s) for inductive los 37000 mA DC at 120 V 2 contact(s) for resistive los 37000 mA DC at 180 V 3 contact(s) for resistive los 37000 mA DC at 60 V 1 contact(s) for resistive los 40000 mA DC at 140 V 3 contact(s) for resistive los 40000 mA DC at 24 V 1 contact(s) for inductive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 70 V 3 contact(s) for inductive los 40000 mA DC at 24 V 1 contact(s) for resistive los 50000 mA DC at 48 V 2 contact(s) for resistive los 50000 mA DC at 48 V 2 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 600	,
30000 mA DC at 60 V 2 contact(s) for inductive los 30000 mA DC at 90 V 3 contact(s) for inductive los 3500 mA DC at 110 V 1 contact(s) for inductive los 3500 mA DC at 220 V 2 contact(s) for inductive los 3500 mA DC at 220 V 2 contact(s) for inductive los 3500 mA DC at 330 V 3 contact(s) for inductive los 37000 mA DC at 120 V 2 contact(s) for resistive los 37000 mA DC at 180 V 3 contact(s) for resistive los 37000 mA DC at 60 V 1 contact(s) for resistive los 40000 mA DC at 140 V 3 contact(s) for resistive los 40000 mA DC at 24 V 1 contact(s) for inductive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 70 V 3 contact(s) for inductive los 40000 mA DC at 24 V 1 contact(s) for resistive los 50000 mA DC at 24 V 1 contact(s) for resistive los 50000 mA DC at 48 V 2 contact(s) for resistive los 50000 mA DC at 48 V 2 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 600	
30000 mA DC at 90 V 3 contact(s) for inductive los 3500 mA DC at 110 V 1 contact(s) for inductive los 3500 mA DC at 220 V 2 contact(s) for inductive los 3500 mA DC at 330 V 3 contact(s) for inductive los 37000 mA DC at 120 V 2 contact(s) for resistive los 37000 mA DC at 180 V 3 contact(s) for resistive los 37000 mA DC at 180 V 3 contact(s) for resistive los 40000 mA DC at 140 V 3 contact(s) for resistive los 40000 mA DC at 140 V 3 contact(s) for resistive los 40000 mA DC at 48 V 1 contact(s) for inductive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 70 V 3 contact(s) for inductive los 40000 mA DC at 24 V 1 contact(s) for resistive los 50000 mA DC at 24 V 1 contact(s) for resistive los 50000 mA DC at 24 V 1 contact(s) for resistive los 50000 mA DC at 48 V 2 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 60000 mA DC at 70 V 3 contact(s) for resistive los 60000 mA DC at 70 V 3 contact(s) for resistive los 60000 mA DC at 70 V 3 contact(s) for resistive los 6	
3500 mA DC at 110 V 1 contact(s) for inductive los 3500 mA DC at 220 V 2 contact(s) for inductive los 3500 mA DC at 330 V 3 contact(s) for inductive los 37000 mA DC at 120 V 2 contact(s) for resistive los 37000 mA DC at 180 V 3 contact(s) for resistive los 37000 mA DC at 180 V 3 contact(s) for resistive los 37000 mA DC at 60 V 1 contact(s) for resistive los 40000 mA DC at 140 V 3 contact(s) for resistive los 40000 mA DC at 24 V 1 contact(s) for inductive los 40000 mA DC at 48 V 1 contact(s) for inductive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 70 V 3 contact(s) for inductive los 40000 mA DC at 95 V 2 contact(s) for resistive los 50000 mA DC at 24 V 1 contact(s) for resistive los 50000 mA DC at 48 V 2 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 60000 mA DC at 70 V 3 contact(s) for resistive los 60	,
3500 mA DC at 220 V 2 contact(s) for inductive los 3500 mA DC at 330 V 3 contact(s) for inductive los 37000 mA DC at 120 V 2 contact(s) for resistive los 37000 mA DC at 180 V 3 contact(s) for resistive los 37000 mA DC at 180 V 3 contact(s) for resistive los 40000 mA DC at 140 V 3 contact(s) for resistive los 40000 mA DC at 24 V 1 contact(s) for inductive los 40000 mA DC at 24 V 1 contact(s) for resistive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 70 V 3 contact(s) for inductive los 40000 mA DC at 95 V 2 contact(s) for resistive los 50000 mA DC at 24 V 1 contact(s) for resistive los 50000 mA DC at 48 V 2 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 60000 mA DC at 70 V 3 contact(s) for resistive los 60	,
3500 mA DC at 330 V 3 contact(s) for inductive los 37000 mA DC at 120 V 2 contact(s) for resistive los 37000 mA DC at 180 V 3 contact(s) for resistive los 37000 mA DC at 180 V 3 contact(s) for resistive los 40000 mA DC at 140 V 3 contact(s) for resistive los 40000 mA DC at 24 V 1 contact(s) for inductive los 40000 mA DC at 48 V 1 contact(s) for resistive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 70 V 3 contact(s) for inductive los 40000 mA DC at 95 V 2 contact(s) for resistive los 50000 mA DC at 24 V 1 contact(s) for resistive los 50000 mA DC at 48 V 2 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 60000 mA DC at 70 V 3 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 60000 mA DC at 70 V 3 contact(s) for resistive los 60	` ,
37000 mA DC at 120 V 2 contact(s) for resistive los 37000 mA DC at 180 V 3 contact(s) for resistive los 37000 mA DC at 60 V 1 contact(s) for resistive los 40000 mA DC at 140 V 3 contact(s) for resistive los 40000 mA DC at 24 V 1 contact(s) for inductive los 40000 mA DC at 24 V 1 contact(s) for resistive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 70 V 3 contact(s) for inductive los 40000 mA DC at 95 V 2 contact(s) for resistive los 50000 mA DC at 24 V 1 contact(s) for resistive los 50000 mA DC at 48 V 2 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 600	,
37000 mA DC at 180 V 3 contact(s) for resistive los 37000 mA DC at 60 V 1 contact(s) for resistive los 40000 mA DC at 140 V 3 contact(s) for resistive los 40000 mA DC at 24 V 1 contact(s) for inductive los 40000 mA DC at 48 V 1 contact(s) for resistive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 70 V 3 contact(s) for inductive los 40000 mA DC at 95 V 2 contact(s) for resistive los 50000 mA DC at 24 V 1 contact(s) for resistive los 50000 mA DC at 48 V 2 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 6000	,
37000 mA DC at 60 V 1 contact(s) for resistive loa 40000 mA DC at 140 V 3 contact(s) for resistive loa 40000 mA DC at 24 V 1 contact(s) for inductive loa 40000 mA DC at 48 V 1 contact(s) for resistive loa 40000 mA DC at 48 V 2 contact(s) for inductive loa 40000 mA DC at 48 V 2 contact(s) for inductive loa 40000 mA DC at 70 V 3 contact(s) for inductive loa 40000 mA DC at 95 V 2 contact(s) for resistive loa 50000 mA DC at 24 V 1 contact(s) for resistive loa 50000 mA DC at 48 V 2 contact(s) for resistive loa 50000 mA DC at 70 V 3 contact(s) for resistive loa 50000 mA DC at 70 V 3 contact(s) for resistive loa 50000 mA DC at 70 V 3 contact(s) for resistive loa 64 mm	,
40000 mA DC at 140 V 3 contact(s) for resistive lot 40000 mA DC at 24 V 1 contact(s) for inductive lot 40000 mA DC at 48 V 1 contact(s) for resistive lot 40000 mA DC at 48 V 2 contact(s) for inductive lot 40000 mA DC at 48 V 2 contact(s) for inductive lot 40000 mA DC at 70 V 3 contact(s) for inductive lot 40000 mA DC at 95 V 2 contact(s) for resistive lot 50000 mA DC at 24 V 1 contact(s) for resistive lot 50000 mA DC at 48 V 2 contact(s) for resistive lot 50000 mA DC at 70 V 3 contact(s) for resistive lot 50000 mA DC at 70 V 3 contact(s) for resistive lot 50000 mA DC at 70 V 3 contact(s) for resistive lot 64 mm	` ,
40000 mA DC at 24 V 1 contact(s) for inductive los 40000 mA DC at 48 V 1 contact(s) for resistive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 48 V 2 contact(s) for inductive los 40000 mA DC at 70 V 3 contact(s) for inductive los 40000 mA DC at 95 V 2 contact(s) for resistive los 50000 mA DC at 24 V 1 contact(s) for resistive los 50000 mA DC at 48 V 2 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 60000 mA DC at 70 V 3 contact(s) for resistive los 64 mm	,
40000 mA DC at 48 V 1 contact(s) for resistive loa 40000 mA DC at 48 V 2 contact(s) for inductive loa 40000 mA DC at 70 V 3 contact(s) for inductive loa 40000 mA DC at 70 V 3 contact(s) for inductive loa 40000 mA DC at 95 V 2 contact(s) for resistive loa 50000 mA DC at 24 V 1 contact(s) for resistive loa 50000 mA DC at 48 V 2 contact(s) for resistive loa 50000 mA DC at 70 V 3 contact(s) for resistive loa 50000 mA DC at 70 V 3 contact(s) for resistive loa 64 mm	,
40000 mA DC at 48 V 2 contact(s) for inductive location 40000 mA DC at 70 V 3 contact(s) for inductive location 40000 mA DC at 95 V 2 contact(s) for resistive location 50000 mA DC at 24 V 1 contact(s) for resistive location 50000 mA DC at 48 V 2 contact(s) for resistive location 50000 mA DC at 70 V 3 contact(s) for resistive location 50000 mA DC at 70 V 3 contact(s) for resistive location 50000 mA DC at 70 V 3 contact(s) for resistive location 50000 mA DC at 70 V 3 contact(s) for resistive location 50000 cycles CAD overall width 64 mm	
40000 mA DC at 70 V 3 contact(s) for inductive los 40000 mA DC at 95 V 2 contact(s) for resistive los 50000 mA DC at 24 V 1 contact(s) for resistive los 50000 mA DC at 48 V 2 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 50000 mA DC at 70 V 3 contact(s) for resistive los 60000	,
40000 mA DC at 95 V 2 contact(s) for resistive loa 50000 mA DC at 24 V 1 contact(s) for resistive loa 50000 mA DC at 24 V 1 contact(s) for resistive loa 50000 mA DC at 48 V 2 contact(s) for resistive loa 50000 mA DC at 70 V 3 contact(s) for resistive loa Mechanical durability 300000 cycles CAD overall width 64 mm	,
50000 mA DC at 24 V 1 contact(s) for resistive loa 50000 mA DC at 48 V 2 contact(s) for resistive loa 50000 mA DC at 70 V 3 contact(s) for resistive loa 50000 mA DC at 70 V 3 contact(s) for resistive loa 300000 cycles CAD overall width 64 mm	,
50000 mA DC at 48 V 2 contact(s) for resistive loa 50000 mA DC at 70 V 3 contact(s) for resistive loa Mechanical durability CAD overall width 50000 mA DC at 48 V 2 contact(s) for resistive loa 50000 mA DC at 70 V 3 contact(s) for resistive loa 60000 mA DC at 70 V 3 contact(s) for resistive loa 50000 mA DC at 70 V 3 contact(s) for resistive loa 50000 mA DC at 70 V 3 contact(s) for resistive loa 50000 mA DC at 70 V 3 contact(s) for resistive loa 50000 mA DC at 70 V 3 contact(s) for resistive loa 50000 mA DC at 70 V 3 contact(s) for resistive loa 50000 mA DC at 70 V 3 contact(s) for resistive loa 50000 mA DC at 70 V 3 contact(s) for resistive loa 60000 mA DC at	,
50000 mA DC at 70 V 3 contact(s) for resistive load Mechanical durability 300000 cycles CAD overall width 64 mm	,
Mechanical durability 300000 cycles CAD overall width 64 mm	,
CAD overall width 64 mm	(1 – 1 1115)
CAD overall height 64 mm	
CAD overall depth 103 mm	
Net weight 0.305 kg	

Environment

IEC 60947-3	
CULus 120 V 3 hp 1 phase CULus 480 V 25 hp 3 phases CULus 240 V 7.5 hp 1 phase CULus 240 V 7.5 hp 3 phases	
TC	
-2555 °C	
-4070 °C	
Class II conforming to IEC 60536 Class II conforming to NF C 20-030	

Offer Sustainability

REACh Regulation	REACh Declaration
REACh free of SVHC	Yes
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
Toxic heavy metal free	Yes
Mercury free	Yes
RoHS exemption information	₫Yes
China RoHS Regulation	☑ China RoHS Declaration
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins
	waste collection and never end up in rubbish bins