

# TeSys LG - enclosure for DOL starter - with 2 pushbuttons

Local distributor code:

402711777 DE1KS217A06

! Discontinued on: 9 Feb 2023

EAN Code: 3389110069648

### ① Discontinued

### Main

Range of product	TeSys	
Range	TeSys	
Device short name	DE1K	
Product or component type	Enclosure	
Device application	Motor	
Material	Polycarbonate	
Device composition	Contactor ordered separately Circuit-breaker ordered separately	
Product compatibility	LG7	
Control type	Push-button start white I Push-button stop black O	

# Complementary

Device mounting	Surface 4 2 Pg 13 + 2 Pg 16 top 4 2 Pg 13 + 2 Pg 16 bottom	
Cable entry number		
Height	165 mm	
Width	175 mm	
Depth	137 mm	
Net weight	0.5 kg	

### **Environment**

IP degree of protection	IP55 conforming to IEC 60529	
IK degree of protection	IK07 conforming to IEC 60529	
Environmental characteristic	Standard environment	
Product certifications	TIKCA	

## **Packing Units**

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	23.000 cm
Package 1 Width	26.000 cm

Package 1 Length	28.000 cm
Package 1 Weight	1.058 kg
Unit Type of Package 2	P06
Number of Units in Package 2	12
Package 2 Height	75.000 cm
Package 2 Width	60.000 cm
Package 2 Length	80.000 cm
Package 2 Weight	20.920 kg

# Logistical informations

Country of origin FR

# **Contractual warranty**

Warranty 18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

#### Environmental Data explained >

How we assess product sustainability >

∇ Environmental footprint	
Carbon footprint (kg.eq.CO2 per CR, Total Life cycle)	107
Environmental Disclosure	Product Environmental Profile

### **Use Better**

Packaging made with recycled cardboard	Yes	
Packaging without single use plastic	Yes	
EU RoHS Directive	Compliant	
SCIP Number	04104e70-ba29-493c-b2cc-b5837d1f879b	
REACh Regulation	REACh Declaration	

### **Use Again**

○ Repack and remanufacture	
Circularity Profile	End of Life Information
Take-back	No