

Item number: INKNXLGE016O000

The LG interface has been specially designed to allow bidirectional control and monitoring of LG VRF systems from a KNX installation. This enables the control of all the indoor units connected to the system, the monitoring of the main AC functions, and access to some internal variables of the outdoor units.



LG to KNX - 16 indoor units

Features and benefits

KNX standard datapoints (DPTs) support KNX standard datapoints (DPTs) are supported, guaranteeing a simple KNX device/system integration.

Outdoor unit signals

Signals assigned to the outdoor unit are available to be used in the integration.

Easy integration with Intesis MAPS
The integration process is quickly and easily managed using

Front cover LED indicators

Front cover LED indicators give information about the Ethernet and serial communication status.

the Intesis MAPS configuration tool.

Automatic identification

A scan function is available for automatic identification of the units present in the VRF system.

Datapoint support

A wide range of monitoring and control datapoints is available.

Configuration tool and interface automatic updates

Both the Intesis MAPS configuration tool and the interface's firmware can receive automatic updates.

External USB port datalogging

Logs containing relevant data can be generated and stored through the interface's external USB port.





General	
Net Width (mm)	88
Net Height (mm)	56
Net Depth (mm)	90
Net Weight (g)	270
Packed Weight (g)	380
Operating Temperature °C Min	-10
Operating Temperature °C Max	60
Storage Temperature °C Min	-30
Storage Temperature °C Max	60
Power Consumption (W)	127
Input Voltage (V)	For DC: 9 36 VDC ±10%, Max: 250 mA For AC: 24 VAC ±10 %, 50-60 Hz, Max: 127 mA Recommended voltage: 24 VDC, Max: 127 mA
Power Connector	3-pole
Configuration	
	Intesis MAPS
Capacity	Up to 16 indoor units.
Capacity Installation Conditions	
	Up to 16 indoor units. This gateway is designed to be mounted inside an enclosure. If the unit is mounted outside an enclosure, precautions should always be taken to prevent electrostatic discharge to the unit. When working inside an enclosure (e.g., making adjustments, setting switches, etc.), typical anti-static precautions should
Installation Conditions	Up to 16 indoor units. This gateway is designed to be mounted inside an enclosure. If the unit is mounted outside an enclosure, precautions should always be taken to prevent electrostatic discharge to the unit. When working inside an enclosure (e.g., making adjustments, setting switches, etc.), typical anti-static precautions should always be followed before touching the unit.
Installation Conditions Content of Delivery	Up to 16 indoor units. This gateway is designed to be mounted inside an enclosure. If the unit is mounted outside an enclosure, precautions should always be taken to prevent electrostatic discharge to the unit. When working inside an enclosure (e.g., making adjustments, setting switches, etc.), typical anti-static precautions should always be followed before touching the unit. Intesis Gateway, Installation Manual, USB Configuration cable.





G	٦n	er	A
יטי	ااب	וטו	a.

Warranty (years) 3 years

Packaging Material Cardboard

Identification and Status

Product ID	INKNXLGE016O000
Country of Origin	Spain
HS Code	8517620000
Export Control Classification Number (ECCN)	EAR99

Physical Features

Connectors / Input / Output	Console port USB.	
LED Indicators		
DIP & Rotary Switches	EIA-485 serial port configuration.	
Battery Description	Manganese Dioxide Lithium button battery.	

Certifications and Standards

ETIM Classification	EC001604
WEEE Category	IT and telecommunications equipment





Use Case



Integration example.

