

Conventional Devices

Sonos LED Base Sounder Beacon

Advanced Fire Technology

The Sonos LED Base Sounder Beacon is an ideal solution for any type of fire alarm application.

Twelve high powered LEDs function with a 95dB sounder for both audio and visual warning that complies with the Disability and Discrimination Act (DDA). The beacon has a unique design that can be seen from every angle including directly below the unit.

It is design to accommodate a variety of detector heads from major manufacturers enabling detection and alarm at the same point. Consequently wiring and installation costs are reduced.

With the optional cover plate it can also be used as a stand alone sounder beacon.



Key Features

- Combined sounder beacon current consumption of less than 10mA
- Unique beacon design for optimised light coverage
- Two large cable entries for quick and simple installation
- Designed to complement a variety of detectors
- 32 distinct alarm tones
- Cover plate (08-18-980686) available for use as a sounder beacon only

Specification

IP Rating	Indoor
Rating	Continuous
Frequency	400-2850Hz
Operating Temp	-10°C to +55°C
Construction	High Impact Polycarbonate
Audibility at 1M	Up to 95dB (A)
Voltage	17-60VDC
Tones	32
Current	8mA
Weight	100g
Compliance	EN54-3 Type A

Order Codes and Options

- | | |
|--------------|---|
| 08-PBS-0017: | Sonos White LED base sounder beacon |
| 08-PBS-0020: | Sonos Optional White LED base sounder cover plate |