# Product data sheet Characteristics

## LGYT1E14

Earth terminal block, Linergy, screw and screwless terminals, 14 holes, 3x25 mmÂ<sup>2</sup> + 11x4 mmÂ<sup>2</sup>, with jumper

#### Main

Range	Linergy
Product or component type	Terminal block
Accessory / separate part category	Connection accessory
Range compatibility	Resi9 enclosure Pragma enclosure Kaedra enclosure enclosure
Colour	Green

## Complementary

Provided equipment	1.0 x jumper	
Enclosure mounting	Flush Surface	
[In] rated current	63 A	
[Ue] rated operational voltage	440 V AC	
Number of terminal blocks	1 earth (screw and screwless terminals) with 14 outgoers	
Distribution block outgoers	3 x 25 mm² for earth 11 x 4 mm² for earth	
Connections - terminals	Screwless terminals (earth) , 11.0 x 4 mm² (flexible with ferrule) Screw terminals (earth) , 3.0 x 25 mm² (flexible) Screwless terminals (earth) , 11.0 x 4 mm² (flexible) Screwless terminals (earth) , 11.0 x 6 mm² (semi-rigid) Screwless terminals (earth) , 11.0 x 6 mm² (rigid) Screw terminals (earth) , 3.0 x 16 mm² (rigid) Screw terminals (earth) , 3.0 x 25 mm² (semi-rigid)	
Free slots	2 for jumper to connect an other terminal block	
Width	67.2 mm	
Height	45.5 mm	
Depth	40.5 mm	
Market segment	Small commercial Residential	

### **Environment**

Ambient air temperature for storage	-2560 °C	
-------------------------------------	----------	--

### Offer Sustainability

Office Oddital lability		
REACh Regulation	REACh Declaration	
REACh free of SVHC	Yes	
EU RoHS Directive	Compliant EPEU RoHS Declaration	
Toxic heavy metal free	Yes	
Mercury free	Yes	
RoHS exemption information	₫Yes	
China RoHS Regulation	China RoHS Declaration	
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins	

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not interested for a set of or determining suitability or intelability of these products for specific user applications. It is the documentation is not integrator to perform the appropriate and complete risk analysis, evaluating of the products with respect to the relevant specific application or use thereof. Neither Schmeider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.