Product data sheet Characteristics

LGYT1E24

Earth terminal block, Linergy, screw and screwless terminals, 24 holes, 3x25 mmÂ² + 21x4 mmÂ², with jumper

I	la	11	r
-			_

Range	Linergy
Product or component type	Terminal block
Accessory / separate part category	Connection accessory
Range compatibility	Resi9 enclosure Pragma enclosure Kaedra enclosure enclosure
Colour	Green

Complementary

Provided equipment	1.0 x jumper	
Enclosure mounting	Flush Surface	
[In] rated current	63 A	
[Ue] rated operational voltage	440 V AC	
Number of terminal blocks	1 earth (screw and screwless terminals) with 24 outgoers	
Distribution block outgoers	3 x 25 mm² for earth 21 x 4 mm² for earth	
Connections - terminals	Screwless terminals (earth) , 21 x 6 mm² (semi-rigid) Screwless terminals (earth) , 21 x 4 mm² (flexible with ferrule) Screw terminals (earth) , 3.0 x 16 mm² (rigid) Screw terminals (earth) , 3.0 x 25 mm² (flexible) Screw terminals (earth) , 3.0 x 25 mm² (semi-rigid) Screwless terminals (earth) , 21 x 6 mm² (rigid) Screwless terminals (earth) , 21 x 4 mm² (flexible)	
Free slots	2 for jumper to connect an other terminal block	
Width	94.2 mm	
Height	45.5 mm	
Depth	40.5 mm	
Market segment	ent Small commercial Residential	

Environment

Ambient air temperature for storage	-2560 °C	

Offer Sustainability

REACh Declaration	
Yes	
Compliant EEU RoHS Declaration	
Yes	
Yes	
€Yes	
☑ China RoHS Declaration	
The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins	

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not inherent or and is not to be used for determining suitability or inhability of these products for specific user applications. It is the dourn aren in integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.