



DATASHEET:-

SIP ISG 1000 Digital Inverter Generator

SIP Part Number 25118

Product Details:

Petrol Engine Driven Inverter Generator.
Pure Sine Wave output for Stable Power Supply.
Compact "Suitcase" Design.
Lightweight & Portable with Reduced Noise.
Economy Engine Switch for Increase Fuel Economy.
1 x USB outlets for Electronic Devices.
Low Oil & "Overload" Indicators.

Specification:

Engine: SIP 60cc Unleaded Petrol
Output Supply: 1 x 230v UK Domestic Socket / 2 x 5v 2A USB
Continuously Rated Output: 900W (0.9kVA)
Maximum Output: 1000W (1kVA)
Fuel Tank Capacity: 3.5 Litres
Max Run Time: 6 Hours
Noise L_wA: 89dB(A)
Noise @ 7mtrs; 1/4 Load: 58dB
Net weight: 13.5KG
1 Year Warranty