



Electrical Test Tools > Electrical Testers >

Fluke 9062 Motor & Phase Rotation Indicator



- 3 phase indication
- Indication of phase rotation
- Indication of motor rotation direction
- Contact free determination of the rotation direction of running



[Electrical Test Tools](#) > [Electrical Testers](#) >

Fluke 9062 Motor & Phase Rotation Indicator

Technical Specifications	
Voltage range	Up to 440 V
Phase Display	120-440 V AC
Frequency range	2-400 Hz
Operating timer	Continuous

Environmental Specifications	
Operating temperature	0 °C to 40 °C
Operating Altitude	Up to 2000m
Humidity (Without Condensation)	15 % to 80 %
Dust/water resistance	IP 40

Safety Specifications	
Electrical Safety	EN 61010, EN 61557-7
Overvoltage category	CAT III, 300 V

Mechanical & General Specifications	
Size	124 x 61 x 27 mm
Weight	1 x 9 V
Batteries	1 x 9 V
Warranty	2 years