DATASHEET - PFGM-63/2/05-A



Residual current circuit breaker (RCCB), 63A, 2pole, 500mA, type A

Part no. PFGM-63/2/05-A Catalog No. 267452



Similar to illustration

Delivery program			
Basic function			Residual current circuit-breakers
Number of poles			2 pole
Application			Residual current circuit-breaker for residential and commercial applications
Rated current	l _n	Α	63
Rated short-circuit strength	I _{cn}	kA	10
Rated fault current	$I_{\Delta N}$	Α	0.5
Туре			Туре А
Tripping		s	non-delayed
Product range			PFGM
Sensitivity			Pulse-current sensitive
Impulse withstand current			Partly surge-proof 250 A

	Technical data			
Standards IC/EN 61008 Rated operational voltage U _u V.C Rated operating voltage U _u V.C 20 Rated frequency f Hz 50 Limit values of the operating voltage V.C 186-284 Sensitivity V.C 196-284 Sensitivity V.M 440 Rated insulation voltage U _i V.M 440 Rated impulse withstand voltage U _i V.M 40 Rated impulse withstand voltage U _i V.M 40 Rated making and breaking capacity / Rated residual making and breaking I _i M _i M _i M _i A 30 Rated making and breaking capacity / Rated residual making and breaking Querations X 400 Reteriorical Querations X 2000 Reteriorical X X-MIX 28493 References X-WIC 284932 Remote control and automatic switching device X X-VIV.2 28296 Compact enclosure X-WIV.2 2276240 Wolchanical X-WIV.2 2276240 <th>Electrical</th> <th></th> <th></th> <th></th>	Electrical			
Name of persistent of protection of voltage Vac Rated operating voltage Vac Rated operating voltage Vac Seat of	Types conform to			IEC/EN 61008
Rated operating voltage V a V AC 20 Rated frequency f 2 V AC 20 Institution voltage F 2 V AC 196-264 Sensitivity Pulse-current sensitive Rated impulse withstand voltage V 40 40 Rated impulse withstand voltage Imp kV 4 Rated making and breaking capacity / Rated residual making and breaking Imp kA 10 Rated making and breaking capacity / Rated residual making and breaking Imp kA 30 References V 4000 4000 References V 20000 20000 References V 2.HK 28452 2.HK 28452 Remote control and automatic switching device V 2.HK 248432 2.HK 248432 Compact enclosure V 2.HK 248432 2.HK 248432	Standards			IEC/EN 61008
Rated prequency Rated frequency Limit values of the operating voltage Test circuit Sensitivity Rated insulation voltage Rated insulation voltage Rated short-circuit strength Rated short-circuit strength Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rate	Rated operational voltage	U _e	V	
Rated frequency Limit values of the operating voltage Test circuit Sensitivity Sensitivity Limit values of the operating voltage Rated inputs withstand voltage Rated inputs withstand voltage Rated short-circuit strength Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated short-circuit strength Rated short-circ		U _e	V AC	
Limit values of the operating voltage Test circuit Sensitivity Test circuit Sensitivity Ui VAC VAC Value-current sensitive Attended insulation voltage Vi Vi Vi Vi Vi Vi Vi Vi Vi V	Rated operating voltage	U _e	V AC	230
Test circuit Senstivity Rated insulation voltage Rated insulation voltage Rated insulation voltage Rated short-circuit strength Rated short-circuit strength Rated short-circuit strength Rated short-circuit strength Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated making and breaking	Rated frequency	f	Hz	50
Sensitivity Rated insulation voltage Rated impulse withstand voltage Rated impulse withstand voltage Rated impulse withstand voltage Rated short-circuit strength Rated short-circuit strength Rated making and breaking capacity / Rated residual making and breaking capacity Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated making and breaking capacity / Rated residual making and breaking Rated short-circuit strength Rated making and breaking Rated short-circuit strength Rated short-circuit strength Rated short-circuit strength Rated making and breaking and breaking Rated short-circuit strength Rated making and breaking and breaking Rated short-circuit strength Rated short-circuit strength Rated making and breaking and breaking Rated making and breaking and breaking Rated making and breaking and breaking Rated short-circuit strength Rated making and breaking and breaking Rated short-circuit strength Rated making and breaking and breaking Rated making and breaking and breaking Rated making and breaking and breaking Rated short-circuit strength Rated sho	Limit values of the operating voltage			
Rated insulation voltage Rated impulse withstand voltage Rated short-circuit strength Rated short-circuit strength Rated short-circuit strength Rated short-circuit strength Rated making and breaking capacity / Rated residual making and breaking capacity Rated making and breaking capacity / Rated residual making and breaking capacity Rated making and breaking capacity / Rated residual making and breaking capacity Rated making and breaking capacity / Rated residual making and breaking capacity Rated making and breaking capacity / Rated residual making and breaking capacity Rated making and breaking capacity / Rated residual making and breaking capacity Rated making and breaking capacity / Rated residual making and breaking capacity Rated making and breaking capacity / Rated residual making and breaking capacity Rated making and breaking capacity / Rated residual making and breaking capacity Rated making and breaking capacity / Rated residual making and breaking capacity Rated making and breaking capacity / Rated residual making and breaking capacity Rated making and breaking capacity / Rated residual making and breaking capacity Rated making and breaking capacity / Rated residual making and breaking capacity Rated making and breaking capacity / Rated residual making and breaking capacity Rated making and breaking capacity / Rated residual making and breaking capacity Rated making and breaking capacity / Rated and solutions capacity Rated making and breaking capacity / Rated and solutions capacity Rated making and breaking capacity / Rated and solutions capacity Rated making and breaking capacity / Rated and solutions capacity Rated making and breaking capacity / Rated and solutions capacity Rated making and breaking capacity / Rated and solutions capacity Rated making and breaking capacity Rated making and breaking capacity Rated and solutions capacity Rated making and breaking capacity Rated and solutions capacity Rated and solutions capacity Rated and solutions capacity Rated	Test circuit		V AC	196 - 264
Rated impulse withstand voltage Rated short-circuit strength Rated making and breaking capacity / Rated residual making and breaking capacity / Rated Rated residual making and breaking capacity / Rated Rated Rated Rated Rated Rated Rated Rated Rated	Sensitivity			Pulse-current sensitive
Rated short-circuit strength Rated making and breaking capacity / Rated residual making and breaking capacity Relectrical Relectrical Operations	Rated insulation voltage	Ui	V	440
Rated making and breaking capacity/ Rated residual making and breaking capacity Image: Capacity Image: Capacity Rated residual making and breaking capacity	Rated impulse withstand voltage	U _{imp}	kV	4
Electrical Operations ≥ 4000 Mechanical Operations ≥ 20000 Mechanical Operations ≥ 20000 Mechanical Operations ≥ 20000 Mechanical Operations ≥ 20000 Mechanical Control installation Z-HK 248432 Tripping signal contact for subsequent installation Z-NHK 248434 Remote control and automatic switching device Z-FW/LP 248296 Compact enclosure KLV-TC-2 276240 Switching interlock IS/SPE-1TE 101911 Sealing cover set IS/SPE-1TE 101911 Standard front dimension Mmm 45 Device height mm 80 Device height mm 80 Mounting Outs attachment with 2 latch positions for DIN-rail IEC/EN 60715 Device of Protection IP20, IP40 with suitable enclosure	Rated short-circuit strength	I _{cn}	kA	10
Electrical Operations ≥ 4000 Mechanical Operations ≥ 20000 References Auxiliary switch for subsequent installation Tripping signal contact for subsequent installation Remote control and automatic switching device Compact enclosure Switching interlock Switching interlock Sealing cover set Vechanical Standard front dimension Device height Built-in width Mounting Degree of Protection	Rated making and breaking capacity / Rated residual making and breaking capacity	$I_m/I_{\Delta m}$	А	630
Mechanical Nechanical Necha	lifespan			
Auxiliary switch for subsequent installation Auxiliary switch for subsequent installation Emote control and automatic switching device Compact enclosure Switching interlock Sealing cover set Vechanical Standard front dimension Device height Built-in width Mounting Degree of Protection Auxiliary switch for subsequent installation Z-HK 248432 Z-NHK 248434 Z-FW/LP 248296 KLV-TC-2 276240 IS/SPE-1TE 101911 SIS/SPE-1TE 101911 SPE-1TE 101911 SPE	Electrical	Operations		≧ 4000
Auxiliary switch for subsequent installation Emote control and automatic switching device Compact enclosure Switching interlock Sealing cover set Mechanical Standard front dimension Built-in width Mounting Degree of Protection Z-HK 248432 Z-NHK 248434 Z-FW/LP 248296 KLV-TC-2 276240 IS/SPE-1TE 101911 Z-RC/AK-2TE 285385 WECHANICAL STANDARD AND AND AND AND AND AND AND AND AND AN	Mechanical	Operations		≧ 20000
Tripping signal contact for subsequent installation Remote control and automatic switching device Compact enclosure Switching interlock Switching interlock Sealing cover set Mechanical Standard front dimension Device height Built-in width Mounting Degree of Protection Z-NHK 248434 Z-FW/LP 248296 KLV-TC-2 276240 IS/SPE-1TE 101911 Z-RC/AK-2TE 285385 MECHANICAL STANDAM	References			
Remote control and automatic switching device Compact enclosure KLV-TC-2 276240 IS/SPE-1TE 101911 Z-RC/AK-2TE 285385 Mechanical Standard front dimension mm 45 Device height mm 80 Built-in width mm 35 (2TE) Quick attachment with 2 latch positions for DIN-rail IEC/EN 60715 Degree of Protection IP20, IP40 with suitable enclosure	Auxiliary switch for subsequent installation			Z-HK 248432
Compact enclosure Switching interlock Switching interlock Sealing cover set Vechanical Standard front dimension Sealing to the eight Substitution width width 2 latch positions for DIN-rail IEC/EN 60715 Substitution width width 2 latch positions for DIN-rail IEC/EN 60715 Substitution width width 2 latch positions for DIN-rail IEC/EN 60715 Substitution width width 2 latch positions for DIN-rail IEC/EN 60715 Substitution width width 2 latch positions for DIN-rail IEC/EN 60715 Substitution width width 2 latch positions for DIN-rail IEC/EN 60715 Substitution width width 2 latch positions for DIN-rail IEC/EN 60715 Substitution width width 2 latch positions for DIN-rail IEC/EN 60715 Substitution width width 2 latch positions for DIN-rail IEC/EN 60715 Substitution width width 2 latch positions for DIN-rail IEC/EN 60715 Substitution width width 2 latch positions for DIN-rail IEC/EN 60715	Tripping signal contact for subsequent installation			Z-NHK 248434
Switching interlock Sealing cover set Z-RC/AK-2TE 285385 Mechanical Standard front dimension mm 45 Device height mm 80 Built-in width mm 35 (2TE) Mounting Degree of Protection IS/SPE-1TE 101911 Z-RC/AK-2TE 285385 Mounting IS/SPE-1TE 101911 Q-IC/AK-2TE 285385 INFO AMOUNTING IMPORTMENT OF THE TOTAL STATE STA	Remote control and automatic switching device			Z-FW/LP 248296
Sealing cover set Mechanical Standard front dimension mm 45 Device height Built-in width Mounting Degree of Protection Z-RC/AK-2TE 285385 T-RC/AK-2TE 285385 A Command of the second of the	Compact enclosure			KLV-TC-2 276240
Mechanical Standard front dimension mm 45 Device height mm 80 Built-in width mm 35 (2TE) Mounting Quick attachment with 2 latch positions for DIN-rail IEC/EN 60715 Degree of Protection IP20, IP40 with suitable enclosure	Switching interlock			IS/SPE-1TE 101911
Standard front dimension mm 45 Device height mm 80 Built-in width mm 35 (2TE) Mounting Quick attachment with 2 latch positions for DIN-rail IEC/EN 60715 Degree of Protection IP20, IP40 with suitable enclosure	Sealing cover set			Z-RC/AK-2TE 285385
Device height mm 80 Built-in width mm 35 (2TE) Mounting Quick attachment with 2 latch positions for DIN-rail IEC/EN 60715 Degree of Protection IP20, IP40 with suitable enclosure	Mechanical			
Built-in width mm 35 (2TE) Mounting Quick attachment with 2 latch positions for DIN-rail IEC/EN 60715 Degree of Protection IP20, IP40 with suitable enclosure	Standard front dimension		mm	45
Mounting Quick attachment with 2 latch positions for DIN-rail IEC/EN 60715 Degree of Protection IP20, IP40 with suitable enclosure	Device height		mm	80
Degree of Protection IP20, IP40 with suitable enclosure	Built-in width		mm	35 (2TE)
	Mounting			Quick attachment with 2 latch positions for DIN-rail IEC/EN 60715
Terminals top and bottom Open mouthed/lift terminals	Degree of Protection			IP20, IP40 with suitable enclosure
	Terminals top and bottom			Open mouthed/lift terminals

Terminal protection		BGV A3, ÖVE-EN 6
Terminal cross-section		
Solid	mm^2	1.5 - 35
Stranded	mm^2	2 x 16
Thickness of busbar material	mm	0.8 - 2
Permissible storage and transport temperatures	°C	-35 - +60
Climatic proofing		25-55°C/90-95% relative humidity according to IEC 60068-2
Thickness of busbar material	mm	
Material thickness	mm	0.8 - 2

Design verification as per IEC/EN 61439

2001gii 10111101111011 110 por 120, 211 01 100			
Technical data for design verification			
Rated operational current for specified heat dissipation	In	Α	63
Heat dissipation per pole, current-dependent	P _{vid}	W	0
Equipment heat dissipation, current-dependent	P _{vid}	W	7.2
Static heat dissipation, non-current-dependent	P _{vs}	W	0
Heat dissipation capacity	P _{diss}	W	0
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	60
			Starting at 40 °C, the max. permissible continuous current decreases by 1.8% for every 1 °C
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			Meets the product standard's requirements.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES			Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.
10.8 Connections for external conductors			Is the panel builder's responsibility.
10.9 Insulation properties			
10.9.2 Power-frequency electric strength			Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage			Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material			Is the panel builder's responsibility.
10.10 Temperature rise			The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function			The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 7.0

Circuit breakers and fuses (EG000020) / Residual current circuit breaker (RCCB) (EC000003)

Electric engineering, automation, process control engineering / Electrical installation, device / Residual current protection system / Residual current circuit breaker (RCCB) (ecl@ss10.0.1-27-14-22-01 [AAB906014])

(00.000.00 2 2. 0 1 1			
Number of poles		2	
Rated voltage	V	230	

Rated current	А	63
Rated fault current	mA	500
Rated insulation voltage Ui	V	440
Rated impulse withstand voltage Uimp	kV	4
Mounting method		DIN rail
Leakage current type		A
Selective protection		No
Short-time delayed tripping		No
Short-circuit breaking capacity (Icw)	kA	10
Surge current capacity	kA	0.25
Frequency		50 Hz
Additional equipment possible		Yes
With interlocking device		Yes
Degree of protection (IP)		IP20
Width in number of modular spacings		2
Built-in depth	mm	69.5
Ambient temperature during operating	°C	-25 - 60
Pollution degree		2
Connectable conductor cross section multi-wired	mm²	1.5 - 16
Connectable conductor cross section solid-core	mm²	1.5 - 35