Specifications



Eaton 185163

Eaton Moeller® series C22 Emergency stop/emergency switching off pushbutton, Palm-tree shape, 45 mm, Turn-to-release function, 2 NC, Cable (black) with non-terminated end, 4 pole, 3.5 m C22-PVT45P-MPI-K02-P65

General specifications	
PRODUCT NAME	Eaton Moeller® series C22 Emergency stop/emergency switching off pushbutton
CATALOG NUMBER	185163
MODEL CODE	C22-PVT45P-MPI-K02-P65
EAN	4015081806485
PRODUCT LENGTH/DEPTH	3597 mm
PRODUCT HEIGHT	45 mm
PRODUCT WIDTH	45 mm
PRODUCT WEIGHT	0.16 kg
CERTIFICATIONS	UL VDE 0660 CSA IEC/EN 60947-5-5 CE CSA Class No.: 321103 CSA File No.: 165628 IEC/EN 60947-5-1 UL 508 CSA-C22.2 No. 14-10 CSA-C22.2 No. 94-91 CSA-C22.2 No. 94.2-07 CE marking UL File No.: E340491
CATALOG NOTES	Contacts with safety function, by positive opening to IEC/EN 60947-5-1



Features & Functions	S
BASE COLOR	Yellow
DESIGN	Palm-tree shaped Classical
FEATURES	Mechanical switch position indication Tamper-proof (according to ISO 13850, EN 418) Positive opening
ILLUMINATION	Non-illuminated
INDICATION	Switch position indication red: Pushbutton actuated Switch position indication green: Pushbutton released
UNLOCKING METHOD	Turn-release

General	
CABLE LENGTH	3.5 m
CABLE MATERIAL	PUR
CONNECTION TO SMARTWIRE-DT	No
CONNECTION TYPE	Cable (black) with non- terminated end, 4 pole
DEGREE OF PROTECTION	NEMA 4X, 13 IP67/IP69K
MOUNTING METHOD	Built-in
MOUNTING POSITION	As required
OPENING DIAMETER	22.5 mm
OPERATING FREQUENCY	300 Operations/h
OVERVOLTAGE CATEGORY	III
POLLUTION DEGREE	3
PRODUCT CATEGORY	RMQ compact solution
RATED IMPULSE WITHSTAND VOLTAGE (UIMP)	800 V AC
SHOCK RESISTANCE	30 g, Mechanical, Shock duration 11 ms
TIGHTENING TORQUE	2 Nm, Threaded ring
ТҮРЕ	Controlled stop pushbutton/emergency-stop button

Climatic environmental conditions	
AMBIENT OPERATING TEMPERATURE - MIN	-30 °C
AMBIENT OPERATING TEMPERATURE - MAX	70 °C
AMBIENT STORAGE TEMPERATURE - MIN	-30 °C
AMBIENT STORAGE TEMPERATURE - MAX	80 °C
CLIMATIC PROOFING	Damp heat, constant, to IEC 60068-2-78 Damp heat, cyclic, to IEC 60068-2-30

Electrical rating	
RATED CONDITIONAL SHORT-CIRCUIT CURRENT (IQ)	1 kA
RATED INSULATION VOLTAGE (UI)	250 V
RATED OPERATIONAL CURRENT (IE) AT DC-13, 24 V	3 A
RATED OPERATIONAL CURRENT (IE) AT AC-15, 24 V	4 A
SHORT-CIRCUIT PROTECTION RATING	Max. 4 A gG/gL, Fuse, Contacts

Actuator	
ACTUATING FORCE	50 N
ACTUATOR COLOR	Red
ACTUATOR DIAMETER	45 mm
ACTUATOR FUNCTION	Turn-to-release
ACTUATOR TRAVEL AND ACTUATION FORCE (DIN EN 60947-5-1)	4.65 mm
KNOB TRAVEL	5.7 mm

Contacts	
CONTROL CIRCUIT RELIABILITY	1 failure per 900,000 switching operations statistically determined, at 17 V DC/7 mA: N/C contact)
FORCE FOR POSITIVE OPENING - MIN	30 N
NUMBER OF CONTACTS (NORMALLY CLOSED CONTACTS)	2
NUMBER OF CONTACTS (NORMALLY OPEN CONTACTS)	0

Resources	
CATALOGUES	eaton-pushbuttons-signal- towers-sensors- assortment-overview- catalog-ca047003en-en- us.pdf
CONTROL TRAVEL DIAGRAM	eaton-operating-adapter- key-operated-actuator- contact-travel-diagram.eps
DECLARATIONS OF CONFORMITY	eaton-emergency-stop- emergency-switching-off- pushbutton-declaration- of-conformity- eu250546en.pdf eaton-emergency-stop- emergency-switching-off- pushbutton-declaration- of-conformity- uk251029en.pdf
	eaton-operating-c22- dimensions-002.eps
DRAWINGS	eaton-operating-button- symbol-002.eps
	eaton-operating-c22-3d-drawing-003.eps
ECAD MODEL	<u>DA-CE-ETN.C22-PVT45P-</u> <u>MPI-K02-P65</u>
FLYERS	eaton-rmq-titan-selection- aid-brochure-fl047002-en- us.pdf
INSTALLATION INSTRUCTIONS	IL047010ZU.pdf
INSTALLATION VIDEOS	Eaton's RMQ compact solution pilot devices
MCAD MODEL	DA-CD- c22 pvt45p open cable
	DA-CS- c22_pvt45p_open_cable
	eaton-rmq-compact-
	solution-flyer-fl047001en- en-us.pdf
SALES NOTES	solution-flyer-fl047001en-
SALES NOTES	solution-flyer-fl047001en- en-us.pdf eaton-rmq-mci-multi- color-light-indicator-flyer-

PROJECT NAME:	
PROJECT NUMBER:	
PREPARED BY:	
DATE:	



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.









