

**ENGLISH** 

### **Datasheet**

# RS Pro Straight 75 $\Omega$ RF Adapter BNC Plug to BNC Plug

RS Stock No: 546-4566



#### **Product Details**

RS Pro RF adapter has BNC plug connector on both the ends that comes with an impedance of 75  $\Omega$ . The RF adapter has straight body orientation and is made of copper contact material.

#### **Features and Benefits**

- Nominal impedance of 75Ω
- Copper contacts
- Straight orientation



## **ENGLISH**

### **Specifications:**

Adapter Type A BNC
Adapter Type B BNC
Adapter Type BNC Plug to BNC Plug

Body Orientation Straight

Body Plating Silver
Contact Material Copper
Contact Plating Silver

 $\begin{array}{ll} \text{Gender A} & \text{Plug} \\ \text{Gender B} & \text{Plug} \\ \text{Impedance} & 75~\Omega \end{array}$ 

Length 31.6±0.5 mm

Operating Frequency 0 to 1 GHz

Body Material Brass
Insulation Material PTFE

Operating Temperature -65 to +165°C

Voltage Rating 500 V