LG8K09N714

TeSys LG - enclosed DOL reversing starter -6...10 A - 400/415 V AC coil



Main	
Range	TeSys
Product name	TeSys LG
Device short name	LG8K
Product or component type	Enclosed DOL reversing starter
Device application	Safety
Utilisation category	AC-3
Device composition	Reversing contactor Circuit-breaker Padlocking device
Motor power kW	4 KW at 400/415 V AC 50/60 Hz 4 KW at 440 V AC 50/60 Hz 1.5 kW at 220/230 V AC 50/60 Hz
Thermal protection adjustment range	610 A
[Uc] control circuit voltage	400/415 V AC 50/60 Hz
Control type	Push-button stop black O Selector switch 2 positions start black I-II Mushroom head push-button emergency stop red

Complementary

Cable entry number	4 2 Pg 13 + 2 Pg 16 top 4 2 Pg 13 + 2 Pg 16 bottom	
Width	175 mm	
Height	165 mm	
Depth	146 mm	
Net weight	1.64 kg	

Environment

Standards	IEC 60947-4-1	
	IEC 60204-1	
Material	Polycarbonate	
IP degree of protection	IP55 conforming to IEC 60529 (for enclosure)	
IK degree of protection	IK07 conforming to IEC 60529	
Environmental characteristic	Standard environment	

Packing Units

Unit Type of Package 1	PCE
------------------------	-----

Offer Sustainability

onor odotamasinty		
REACh free of SVHC	Yes	
EU RoHS Directive	Compliant EEU RoHS Declaration	
Toxic heavy metal free	Yes	
Mercury free	Yes	
RoHS exemption information	€Yes	
China RoHS Regulation	☑ China RoHS Declaration	
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins	

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein.
This documentation is not intended as a substitute for and is not to be used for determining suitability of these products for specific user applications.
It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Warranty 18 months