# RE22R2DMR

Symmetrical Flashing Timing Relay - 0.05s... 300h - 24...240V AC/DC - 2C/O



#### Main

man	
Range of product	Zelio Time
Product or component type	Modular timing relay
Discrete output type	Relay
Device short name	RE22
Nominal output current	8 A

## Complementary

Contacts type and composition	<ul><li>1 C/O timed or instantaneous contact, cadmium free</li><li>1 C/O timed contact, cadmium free</li></ul>
Time delay type	D
	Dw
Time delay range	0.33 s
	110 s 0.051 s
	330 s
	10100 s
	30300 s
	330 min
	30300 min 330 h
	30300 h
Control type	External potentiometer
	Diagnostic button Rotary knob
[Us] rated supply voltage	24240 V AC/DC at 50/60 Hz
Release input voltage	<= 2.4 V
Voltage range	0.851.1 Us
Supply frequency	5060 Hz (+/- 5 %)
Connections - terminals	Screw terminals : 2 x 0.22 x 1.5 mm², AWG 24AWG 16 flexible cable with ca-
Connections - terminals	ble end
	Screw terminals: 1 x 0.21 x 2.5 mm², AWG 24AWG 14 flexible cable with ca-
	ble end
	Screw terminals : 2 x 0.52 x 2.5 mm², AWG 20AWG 14 solid cable without cable end
	Screw terminals : 1 x 0.51 x 3.3 mm², AWG 20AWG 12 solid cable without
	cable end
Tightening torque	0.61 N.m conforming to IEC 60947-1
Housing material	Self-extinguishing
Repeat accuracy	+/- 0.5 % conforming to IEC 61812-1
Temperature drift	+/- 0.05 %/°C
Voltage drift	+/- 0.2 %/V
Setting accuracy of time delay	+/- 10 % of full scale at 25 °C conforming to IEC 61812-1
Control signal pulse width	30 ms 100 ms (with load in parallel)
Insulation resistance	100 MOhm at 500 V DC conforming to IEC 60664-1
Recovery time	120 ms (on de-energisation)
Immunity to microbreaks	<= 10 ms
Power consumption in VA	3 VA at 240 V AC


Power consumption in W	1.5 W at 240 V DC
Switching capacity in VA	2000 VA
Minimum switching current	10 mA 5 V DC
Maximum switching current	8 A
Maximum switching voltage	250 V AC
Electrical durability	100000 cycles for 2 A at 24 V DC-1
coarour durability	100000 cycles for 8 A at 250 V AC-1
Mechanical durability	10000000 cycles
Rated impulse withstand voltage	5 kV for 1.250 μs conforming to IEC 60664-1
Power on delay	< 100 ms
Creepage distance	4 kV/3 conforming to IEC 60664-1
Overvoltage category	III conforming to IEC 60664-1
Mounting position	Any position
Mounting support	35 mm DIN rail conforming to EN/IEC 60715
Status LED	Yellow LED (slow flashing) for timing in progress and output relay energised Yellow LED (fast flashing) for timing in progress and output relay de-energised Yellow LED (steady) for output relay energised Green LED backlight (steady) for dial pointer indication
Product weight	0.105 kg
Environment	
Dielectric strength	2.5 kV for 1 mA/1 minute at 50 Hz between relay output and power supply with basic insulation conforming to IEC 61812-1
Standards	IEC 61812-1 UL 508
Directives	2004/108/EC - electromagnetic compatibility 2006/95/EC - low voltage directive
	CE CSA GL UL RCM EAC
Ambient air temperature for operation	China RoHS -2060 °C
	-2000 °C
Ambient air temperature for storage	IP50 (front panel) conforming to IEC 60529
IP degree of protection	IP30 (front parier) conforming to IEC 60529 IP40 (housing) conforming to IEC 60529
Pollution degree	3 conforming to IEC 60664-1
Vibration resistance	20 m/s² (f = 10150 Hz) conforming to IEC 60068-2-6
Shock resistance	5 gn (in operation) (duration = 11 ms) conforming to IEC 60068-2-27 15 gn (not operating) (duration = 11 ms) conforming to IEC 60068-2-27
Relative humidity	95 % at 2555 °C
Electromagnetic compatibility	Immunity to microbreaks and voltage drops (test level: 100 % - 20 ms) conforming to IEC 61000-4-11 Immunity to microbreaks and voltage drops (test level: 30 % - 500 ms) conforming to IEC 61000-4-11 Fast transient bursts (test level: 2 kV, level 3 - direct contact) conforming to IEC 61000-4-4 Conducted RF disturbances (test level: 10 V, level 3 - 0.1580 MHz) conforming to IEC 61000-4-6 Radiated radio-frequency electromagnetic field immunity test (test level: 10 V/m, level 3 - 80 MHz1 GHz) conforming to IEC 61000-4-3 Electrostatic discharge (test level: 8 kV, level 3 - air discharge) conforming to IEC 61000-4-2 Electrostatic discharge (test level: 6 kV, level 3 - contact discharge) conforming to IEC 61000-4-2 Surge immunity test (test level: 2 kV, level 3 - common mode) conforming to IEC 61000-4-5 Surge immunity test (test level: 1 kV, level 3 - differential mode) conforming to IEC 61000-4-5 Fast transients immunity test (test level: 1 kV, level 3 - capacitive connecting clip) conforming to IEC 61000-4-4



# Product data sheet Dimensions Drawings

# RE22R2DMR


## **Dimensions**



# Product data sheet Connections and Schema

# RE22R2DMR

# Wiring Diagram



# RE22R2DMR

#### Function D: Symmetrical Flashing Relay (Starting Pulse Off)


### Description

On energisation of power supply, output(s) R starts at its/their initial state for timing duration T then change(s) to output(s) R close(s) for the same timing duration T.This cycle is repeated indefintely until power supply removal. Specially for RE17\*, RE22R2AMU, RE22R2MMW, RE22R2MMU, RE22R2MJU, this D function can only be initiated by energizing Y1 permanently. The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").


Function: 1 Output




Function: 2 Outputs



Function: 1 Output with Retrigger / Restart Control



Function: 2 Output with Retrigger / Restart Control




Function DW: Symmetrical Flashing Relay (Starting Pulse Off) & With Retrigger / Restart Control


### Description

On energisation of power supply, output(s) R starts at its/their initial state for timing duration T then change(s) to output(s) R close(s) for the same timing duration T.This cycle is repeated indefintely until power supply removal. Specially for RE17\*, RE22R2AMU, RE22R2MMW, RE22R2MMU, RE22R2MJU, this D function can only be initiated by energizing Y1 permanently. The second output (R2) can be either timed (when set to "TIMED") or instantaneous (when set to "INST").

Function: 1 Output



## Function: 2 Outputs



## Legend

Relay de-energised Relay energised Output open Output closed

U Supply

T Timing period

R1/ 2 timed outputs

R2 The second output is instantaneous if the right position is selected inst.

Y1 Retrigger / Restart control