

Datasheet

Volt Stick SOUND
Art-no 482-080



The Volt Stick SOUND is an instrument for safely checking the presence of an AC voltage in cables, wall sockets, fuses junction boxes etc.

No current flow is needed for correct operation. Voltage indication with both sound and light signal.

Low battery indicator. When the sound indicator doesn't appear, when measuring, the batteries should be changed.

Examples of applications areas:

- Locating breaks in cables outside the insulation.
- Detecting blown fuses in fuse or distribution boxes.
- Distinguishing between live and neutral in single and three phase installations.
- Identifying live cables in junction boxes.
- Checking connected switches.
- Locating faulty lamps in series connections (Christmas tree lights).

Technical Specifications:	
Voltage range:	230 VAC
Power supply:	2 x AAA (LR03) batteries (included)
Altitude:	< 2000 m
RH:	80% @ 30°C, 50% @ 40°C
Operating temp:	-10° - +50°C
Overvoltage:	CAT III 1000V
Weight:	40g
Dimensions:	146 mm x Ø max 22mm
Approvals:	CE IEC 61010-1
Material:	Pa6, PP COP

