

# WL12GC-3P2472A00 W12G

SMALL PHOTOELECTRIC SENSORS

**SICK**Sensor Intelligence.



#### Ordering information

Туре	Part no.
WL12GC-3P2472A00	1054087

Other models and accessories → www.sick.com/W12G

Illustration may differ



#### Detailed technical data

#### **Features**

Device type	Photoelectric sensors
Sensor/ detection principle	Photoelectric retro-reflective sensor, autocollimation
Dimensions (W x H x D)	15.5 mm x 48.5 mm x 42 mm
Housing design (light emission)	Rectangular
Sensing range max.	0 m 4 m
Sensing range	0 m 4 m <sup>1)</sup>
Type of light	Visible red light
Light source	PinPoint LED <sup>2)</sup>
Light spot size (distance)	Ø 25 mm (1.5 m)
Wave length	660 nm
Adjustment	IO-Link <sup>3)</sup> Single teach-in button
Pin 2 configuration	External input, Teach-in input, Sender off input, Detection output, logic output, Device contamination alarm output
AutoAdapt	<b>√</b>
Special applications	Detecting transparent objects

<sup>&</sup>lt;sup>1)</sup> Reflector PL80A.

 $<sup>^{2)}</sup>$  Average service life: 100,000 h at TU = +25 °C.

 $<sup>^{3)}\,\</sup>text{Mode I, }10~\%$  attenuation.

#### Mechanics/electronics

Supply voltage	10 V DC 30 V DC <sup>1)</sup>
Ripple	< 5 V <sub>pp</sub> <sup>2)</sup>
Current consumption	30 mA <sup>3)</sup>
Switching output	PNP
Switching mode	Light/dark switching
Signal voltage PNP HIGH/LOW	Approx. $V_S - 2.5 V / 0 V$
Output current I <sub>max.</sub>	≤ 100 mA
Response time Q/ on Pin 2	200 μs 300 μs <sup>4) 5)</sup>
Switching frequency	1,500 Hz <sup>6)</sup>
Switching frequency Q / to pin 2	≤ 1,500 Hz <sup>7)</sup>
Attenuation along light beam	> 8 %
Connection type	Male connector M12, 4-pin
Circuit protection	A <sup>8)</sup> B <sup>9)</sup> C <sup>10)</sup> D <sup>11)</sup>
Protection class	III
Weight	120 g
Polarisation filter	✓
Housing material	Metal, zinc diecast
Optics material	Plastic, PMMA
Enclosure rating	IP66 IP67
Special feature	Detecting transparent objects
Ambient operating temperature	-40 °C +60 °C
Ambient temperature, storage	-40 °C +75 °C
UL File No.	NRKH.E181493 & NRKH7.E181493
Repeatability Q/ on Pin 2:	100 μs <sup>5)</sup>

 $<sup>^{1)}</sup>$  Limit values when operated in short-circuit protected network: max. 8 A.

#### Communication interface

Communication interface	IO-Link V1.1
Communication Interface detail	COM2 (38,4 kBaud)
Cycle time	2.3 ms

 $<sup>^{2)}</sup>$  May not exceed or fall below  $\mathrm{U}_{\mathrm{V}}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Signal transit time with resistive load.

 $<sup>^{5)}</sup>$  Valid for Q  $\backslash$  on Pin2, if configured with software.

<sup>6)</sup> With light/dark ratio 1:1.

 $<sup>^{7)}</sup>$  With light / dark ratio 1:1, valid for Q \ on Pin2, if configured with software.

 $<sup>^{8)}</sup>$  A = V<sub>S</sub> connections reverse-polarity protected.

 $<sup>^{9)}</sup>$  B = inputs and output reverse-polarity protected.

 $<sup>^{10)}</sup>$  C = interference suppression.

 $<sup>^{11)}</sup>$  D = outputs overcurrent and short-circuit protected.

Process data length	16 Bit
Process data structure	Bit 0 = switching signal $Q_{L1}$ Bit 1 = switching signal $Q_{L2}$ Bit 2 15 = empty
VendorID	26
DeviceID HEX	0x8000F2
DeviceID DEC	8388850

#### **Smart Task**

Base logics
Direct AND OR WINDOW Hysteresis
Deactivated On delay Off delay ON and OFF delay Impulse (one shot)
Yes
SIO Direct: 1500 Hz $^{1)}$ SIO Logic: 1500 Hz $^{2)}$ IOL: 1100 Hz $^{3)}$
SIO Direct: 200 $\mu$ s 300 $\mu$ s <sup>1)</sup> SIO Logic: 400 $\mu$ s 500 $\mu$ s <sup>2)</sup> IOL: 400 $\mu$ s 750 $\mu$ s <sup>3)</sup>
SIO Direct: 100 $\mu$ s <sup>1)</sup> SIO Logic: 100 $\mu$ s <sup>2)</sup> IOL: 350 $\mu$ s <sup>3)</sup>
Switching output
Switching output

<sup>1)</sup> SIO Direct: sensor operation in standard I/O mode without IO-Link communication and without using internal sensor logic or time parameters (set to "direct"/"deactivated").

#### Diagnosis

Status inform	ation	
	Device status	Yes
	Quality of teach	Yes
	Quality of run	Yes, Contamination display

#### Classifications

ECI@ss 5.0	27270902
ECI@ss 5.1.4	27270902
ECI@ss 6.0	27270902
ECI@ss 6.2	27270902
ECI@ss 7.0	27270902

<sup>2)</sup> SIO Logic: Sensor operation in standard I/O mode without IO-Link communication. Sensor-internal logic or timing parameters plus Automation Functions used.

<sup>3)</sup> IOL: Sensor operation with full IO-Link communication and usage of logic, timing and Automation Function parameters.


ECI@ss 8.0	27270902
ECI@ss 8.1	27270902
ECI@ss 9.0	27270902
ECI@ss 10.0	27270902
ECI@ss 11.0	27270902
ETIM 5.0	EC002717
ETIM 6.0	EC002717
ETIM 7.0	EC002717
ETIM 8.0	EC002717
UNSPSC 16.0901	39121528

### Connection diagram

Cd-367




# Light spot size



All dimensions in mm (inch)

#### Sensing range diagram

#### WL12G-3




- Sensing range max.
- ① Reflector PL80A
- ② Reflector C110A
- 3 Reflector P250F
- 4 Reflector PL50A
- ⑤ Reflector PL40A
- 6 Reflector PL30A
- ⑦ Reflector PL20A
- ® Reflective tape REF-IRF-56

#### **Functions**

Teach-in-Modus für Ob- jekte / Teach-in mode for objects	Lichtdämpfung /	Objekttyp /	Teach-in-Zeit / Teach-in time	Ext. Teach-in über Lei- tung / Ext. cable teach-in	Anzeige-LED / LED indicator
I	10 %	PET-Flasche / Folie /Glas / PET-Flasche / Folie/ glas	15s	30 100 ms	grün / green
II	18 %	Farbglasflaschen/ Colored glass bottles	5 10 s	100 200 ms	blau / blue


#### Adjustments

#### Teach-in



- ② LED indicator yellow: Status of received light beam
- ③ Green LED indicator: power on, teach-in mode IBlue LED indicator: teach-in mode II
- Single teach-in button, Function 1: teach-in sensitivity on reflector, Function 2: change operation/teach-in mode

#### Dimensional drawing (Dimensions in mm (inch))



- ① Optical axis
- ② LED indicator yellow: Status of received light beam
- 3 LED indicator green: Supply voltage active
- ④ M4 threaded mounting hole, 4 mm deep
- ⑤ Mounting hole, Ø 4.2 mm
- ⑤ Sensitivity setting: single teach-in button
- $\ensuremath{\ensuremath{\,\bigcirc}}$  Connection

#### Recommended accessories

Other models and accessories → www.sick.com/W12G

	Brief description	Туре	Part no.		
Mounting brackets and plates					
	Universal mounting bracket for reflectors, steel, zinc coated	BEF-WN-REFX	2064574		
Plug connecto	ors and cables				
	Head A: female connector, M12, 4-pin, straight, A-coded Head B: Flying leads Cable: Sensor/actuator cable, PVC, unshielded, 5 m	YF2A14- 050VB3XLEAX	2096235		
	Head A: male connector, M12, 4-pin, straight Head B: - Cable: unshielded	STE-1204-G	6009932		
Reflectors					
	Fine triple reflector, screw connection, suitable for laser sensors, 52 mm x 62 mm, PM-MA/ABS, Screw-on, 2 hole mounting	P250F	5308843		

#### Recommended services

Additional services → www.sick.com/W12G

	Туре	Part no.
Function Block Factory		
• <b>Description:</b> The Function Block Factory supports common programmable logic controllers (PLCs) from various manufacturers, such as Siemens, Beckhoff, Rockwell Automation and B&R. More information on the FBF can be found <a href="https://fbf.cloud.sick.com" target="_blank">here</a> .	Function Block Factory	On request

## SICK AT A GLANCE

SICK is one of the leading manufacturers of intelligent sensors and sensor solutions for industrial applications. A unique range of products and services creates the perfect basis for controlling processes securely and efficiently, protecting individuals from accidents and preventing damage to the environment.

We have extensive experience in a wide range of industries and understand their processes and requirements. With intelligent sensors, we can deliver exactly what our customers need. In application centers in Europe, Asia and North America, system solutions are tested and optimized in accordance with customer specifications. All this makes us a reliable supplier and development partner.

Comprehensive services complete our offering: SICK LifeTime Services provide support throughout the machine life cycle and ensure safety and productivity.

For us, that is "Sensor Intelligence."

# **WORLDWIDE PRESENCE:**

Contacts and other locations -www.sick.com

