SIEMENS

Data sheet

6ES7522-5HH00-0AB0



SIMATIC S7-1500, digital output module DQ 16x 230V AC/2A ST; relay 16 channels in groups of 2; 4 A per group; switching cycle counter for integrated relay, diagnostics; substitute value: the module supports the safety-oriented shutdown of load groups up to SIL1 according to EN IEC 62061:2021 and Category 2 / PL c according to EN ISO 13849-1:2015. front connector (screw terminals or push-in) to be ordered separately

Figure similar

General information	
Product type designation	DQ 16x 230 V AC/2 A ST (relay)
HW functional status	FS01
Firmware version	V1.1.0
• FW update possible	Yes
Product function	
• I&M data	Yes; I&M0 to I&M3
Isochronous mode	No
Prioritized startup	Yes
Engineering with	
 STEP 7 TIA Portal configurable/integrated from version 	V13 SP1 / -
 STEP 7 configurable/integrated from version 	V5.5 SP3 / -
 PROFIBUS from GSD version/GSD revision 	V1.0 / V5.1
 PROFINET from GSD version/GSD revision 	V2.3 / -
Operating mode	
• DQ	Yes
 DQ with energy-saving function 	No
• PWM	No
Oversampling	No
• MSO	Yes
 Integrated operating cycle counter 	Yes; FW V1.1.0 or higher
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	185 mA
output voltage / header	
Rated value (AC)	230 V; 24 V DC to 120 V DC / 24 V AC to 230 V AC
Power	
Power available from the backplane bus	0.8 W
Power loss	
Power loss, typ.	5 W
Digital outputs	
Type of digital output	Relays
Number of digital outputs	16
Current-sinking	Yes
Current-sourcing	Yes

Digital outputs, parameterizable	Vac
Digital outputs, parameterizable	Yes
Short-circuit protection	No
Controlling a digital input	Yes -
Size of motor starters according to NEMA, max.	5
Switching capacity of the outputs	
• on lamp load, max.	50 W (230 V AC), 5 W (24 V DC)
Output current	
for signal "1" rated value	2 A
• for signal "1" permissible range, min.	10 mA; 10 V
• for signal "1" permissible range, max.	2 A; thermal continuous current
• for signal "0" residual current, max.	0 A
Parallel switching of two outputs	
 for logic links 	Yes
 for uprating 	No
 for redundant control of a load 	Yes
Switching frequency	
 with resistive load, max. 	1 Hz
 with inductive load, max. 	0.5 Hz
● on lamp load, max.	1 Hz
Total current of the outputs	
 Current per channel, max. 	2 A; see additional description in the manual
 Current per group, max. 	4 A; see additional description in the manual
Current per module, max.	32 A; see additional description in the manual
Relay outputs	
 Number of relay outputs 	16
 Rated supply voltage of relay coil L+ (DC) 	24 V
 Current consumption of relays (coil current of all relays), typ. 	150 mA
 external protection for relay outputs 	Miniature circuit breaker B10 / B16
 Contact connection (internal) 	No
 Number of operating cycles, max. 	see additional description in the manual
 Relay approved acc. to UL 508 	No
Switching capacity of contacts	
— with inductive load, max.	2 A; see additional description in the manual
 — with inductive load, max. — with resistive load, max. 	2 A; see additional description in the manual2 A; see additional description in the manual
— with resistive load, max.	
— with resistive load, max. Cable length	2 A; see additional description in the manual
 with resistive load, max. Cable length shielded, max. 	2 A; see additional description in the manual 1 000 m
 — with resistive load, max. Cable length shielded, max. unshielded, max. 	2 A; see additional description in the manual 1 000 m
 — with resistive load, max. Cable length shielded, max. unshielded, max. Interrupts/diagnostics/status information 	2 A; see additional description in the manual 1 000 m 600 m
	2 A; see additional description in the manual 1 000 m 600 m
	2 A; see additional description in the manual 1 000 m 600 m Yes
	2 A; see additional description in the manual 1 000 m 600 m Yes Yes
 with resistive load, max. Cable length shielded, max. unshielded, max. Interrupts/diagnostics/status information Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt 	2 A; see additional description in the manual 1 000 m 600 m Yes Yes
 with resistive load, max. Cable length shielded, max. unshielded, max. Interrupts/diagnostics/status information Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses 	2 A; see additional description in the manual 1 000 m 600 m Yes Yes Yes
 with resistive load, max. Cable length shielded, max. unshielded, max. Interrupts/diagnostics/status information Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage 	2 A; see additional description in the manual 1 000 m 600 m Yes Yes Yes Yes
 with resistive load, max. Cable length shielded, max. unshielded, max. Interrupts/diagnostics/status information Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break 	2 A; see additional description in the manual 1 000 m 600 m Yes Yes Yes Yes No
 with resistive load, max. Cable length shielded, max. unshielded, max. Interrupts/diagnostics/status information Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit 	2 A; see additional description in the manual 1 000 m 600 m Yes Yes Yes Yes No
 with resistive load, max. Cable length shielded, max. unshielded, max. unshielded, max. Interrupts/diagnostics/status information Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED	2 A; see additional description in the manual 1 000 m 600 m Yes Yes Yes Yes No No
 with resistive load, max. Cable length shielded, max. unshielded, max. unshielded, max. Interrupts/diagnostics/status information Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED 	2 A; see additional description in the manual 1 000 m 600 m Yes Yes Yes Yes No No Yes; green LED
 with resistive load, max. Cable length shielded, max. unshielded, max. Interrupts/diagnostics/status information Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED 	2 A; see additional description in the manual 1 000 m 600 m Yes Yes Yes Yes Yes Yes Yes Yes
 with resistive load, max. Cable length shielded, max. unshielded, max. inshielded, max. Interrupts/diagnostics/status information Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED MAINT LED 	2 A; see additional description in the manual 1 000 m 600 m Yes Yes Yes Yes Yes Yes; green LED Yes; Yellow LED Yes; green LED Yes; green LED
 with resistive load, max. Cable length shielded, max. unshielded, max. Interrupts/diagnostics/status information Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED MAINT LED Monitoring of the supply voltage (PWR-LED) 	2 A; see additional description in the manual 1 000 m 600 m Yes Yes Yes Yes Yes Yes Yes Yes
 with resistive load, max. Cable length shielded, max. unshielded, max. Interrupts/diagnostics/status information Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED MAINT LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics 	2 A; see additional description in the manual 1 000 m 600 m Yes Yes Yes Yes Yes Yes Yes Yes
 with resistive load, max. Cable length shielded, max. unshielded, max. Interrupts/diagnostics/status information Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED MAINT LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics 	2 A; see additional description in the manual 1 000 m 600 m Yes Yes Yes Yes Yes Yes No No Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; green LED Yes; green LED Yes; green LED Yes; green LED No
 with resistive load, max. Cable length shielded, max. unshielded, max. Interrupts/diagnostics/status information Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED MAINT LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics 	2 A; see additional description in the manual 1 000 m 600 m Yes Yes Yes Yes Yes Yes Yes Yes
 with resistive load, max. Cable length shielded, max. unshielded, max. Interrupts/diagnostics/status information Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED MAINT LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics Potential separation channels	2 A; see additional description in the manual 1 000 m 600 m Yes Yes Yes Yes No No Yes; green LED Yes; red LED Yes; Yellow LED Yes; green LED Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; green LED Yes; green LED
 with resistive load, max. Cable length shielded, max. unshielded, max. inshielded, max. Interrupts/diagnostics/status information Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED MAINT LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics Potential separation channels between the channels 	2 A; see additional description in the manual 1 000 m 600 m Yes Yes Yes Yes Yes Yes No No Yes; green LED Yes; green LED No Yes; green LED No No
 with resistive load, max. Cable length shielded, max. unshielded, max. Interrupts/diagnostics/status information Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED MAINT LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics Potential separation channels between the channels, in groups of 	2 A; see additional description in the manual 1 000 m 600 m Yes Yes Yes Yes Yes No No Yes; green LED Yes; red LED Yes; green LED No No
 with resistive load, max. Cable length shielded, max. unshielded, max. inshielded, max. Interrupts/diagnostics/status information Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Diagnostics indication LED RUN LED ERROR LED MAINT LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics Potential separation channels between the channels 	2 A; see additional description in the manual 1 000 m 600 m Yes Yes Yes Yes Yes Yes No No Yes; green LED Yes; green LED No Yes; green LED No No

Permissible potential difference	
between different circuits	250 V AC between the channels and the supply voltage L+; 250 V AC between the channels and the backplane bus; 500 V AC between the channels
Isolation	
Isolation tested with	Between channels: 3 100 V DC; between channels backplane bus: 3 100 V DC; between L+ and backplane bus: 707 V DC (type test)
Standards, approvals, certificates	
Suitable for safety functions	No
Suitable for safety-related tripping of standard modules	Yes; From FS02
Highest safety class achievable for safety-related tripping of s	tandard modules
 Performance level according to ISO 13849-1 	PL c
 Category according to ISO 13849-1 	Cat. 2
Ambient conditions	
Ambient temperature during operation	
 horizontal installation, min. 	-25 °C; From FS02
 horizontal installation, max. 	60 °C
 vertical installation, min. 	-25 °C; From FS02
 vertical installation, max. 	40 °C
Dimensions	
Width	35 mm
Height	147 mm
Depth	129 mm
Weights	
Weight, approx.	350 g

last modified:

8/16/2023 🖸