# Product data sheet
## Characteristics

# LV426900
auxiliary contact (spring) SDx - 2 NO/NC for ELCB



## Main

| | |
|---|---|
| Device short name | SDx |
| Product or component type | Auxiliary contact |
| Range compatibility | Compact VigiCompact NSXm |
| Signal contacts composition | 1 NO/NC for fault<br>1 NO/NC for alarm |

## Complementary

| | |
|---|---|
| Fault type | Earth leakage<br>Overload |
| Local signalling | 1 LED green for ON status<br>2 LEDs red for output status |
| [Ue] rated operational voltage | 24...240 V AC/DC |
| [Ie] rated operational current | Utilisation category AC-15 : 0.3 A network: AC 50/60 Hz at 250 V<br>Utilisation category AC-15 : 1.74 A network: AC 50/60 Hz at 230 V<br>Utilisation category DC-13 : 0.3 A at 160 V<br>Utilisation category DC-13 : 2.08 A at 24 V<br>Utilisation category DC-13 : 5 A at 10 V<br>Utilisation category AC-15 : 5 A network: AC 50/60 Hz at 80 V |
| Auxiliary connection terminal | Spring 0.5...1.5 mm² copper |
| Wire stripping length | 8 mm |