

F204 A S-125/0,5



F204 A S-125/0,5 Residual Current Circuit Breaker



General Information

Extended Product Type	F204 A S-125/0,5
Product ID	2CSF204201R4950
EAN	8012542968405
Catalog Description	F204 A S-125/0,5 Residual Current Circuit Breaker
Long Description	The RCCBs F200 series assures protection to people and installations against fault current to earth. A large offer for standard instantaneous and selective AC and A types is completed with some configurations for special applications.

Ordering

Minimum Order Quantity	1 piece
Customs Tariff Number	85363030

Popular Downloads

Data Sheet, Technical Information	9AKK107046A0424
Instructions and Manuals	Manual sheet inside the box

Dimensions

Product Net Width	0.072 m
Product Net Height	0.085 m
Product Net Depth / Length	0.069 m
Product Net Weight	0.500 kg

Technical

Standards	IEC/EN 61008
Operating Characteristic	Selective
Type of Residual Current	A type
Rated Residual Current	500 mA
Rated Current (I_n)	125 A
Number of Poles	4
Position of Neutral Terminals	Right
Power Loss	at Rated Operating Conditions per Pole 7.5 W

Environmental

Ambient Air Temperature	Operation -25 ... +40 °C Storage -40 ... +70 °C
RoHS Status	Following EU Directive 2011/65/EU

Certificates and Declarations (Document Number)

Declaration of Conformity - CE	9AKK106713A5602
Environmental Information	Refer to RoHS
Instructions and Manuals	Manual sheet inside the box
RoHS Information	2CSC423001K2702

Container Information

Package Level 1 Units	1 piece
Package Level 1 Width	0.073 m
Package Level 1 Height	0.078 m
Package Level 1 Depth / Length	0.09 m
Package Level 1 Gross Weight	0.525 kg
Package Level 1 EAN	8012542968405

Classifications

Object Classification Code	Q
ETIM 4	EC000003 - Residual current circuit breaker (RCCB)
ETIM 5	EC000003 - Residual current circuit breaker (RCCB)
ETIM 6	EC000003 - Residual current circuit breaker (RCCB)
ETIM 7	EC000003 - Residual current circuit breaker (RCCB)

Categories

Low Voltage Products and Systems → Modular DIN Rail Products → Residual Current Devices RCDs → Residual Current Devices RCDs

