


Metrology- 1 phase power meter

Status: Available Data sheet created: 01.07.2025

Item Number: 2800220 - **Serie:** SensAct - **EAN:** 9008662014176



- ✓ 1-phase power meter AC up to 800V and 300A and DC up to 1000V and 400A with Modbus RTU / RS485 interface
- ✓ Frequency range: DC or 1 to 400Hz
- ✓ Measured values: Irms, Vrms, Watt, VAR, VA, Vpk, Ipk, Frequency, Cosφ, Energy measurement bidirectional, THD
- ✓ DIN rail mounting

Description

Precise and reliable reading of mechanical, electrical and electronic measured values with analogue and digital evaluation options.

General information

Short description	1-phase power meter 300A/1000V with Modbus RTU / RS485
Item Number	2800220
EAN	9008662014176
Main category	Measurement Technology
Series	SensAct
Type	S9XM300A1000VM
Supply	9-30V DC



Ambient conditions and general specifications

Pollution degree	2, pollution level can be increased by installation in suitable enclosures (according to IEC 60664-1)
-------------------------	---

Logistics

Minimum Quantity	1
Tariff Number	90303370
EAN	9008662014176
Country of Origin	IT
Product Weight (g)	377

Available declarations / conformities

UL	✓
c(UL)	✓
REACH	Open document
WEEE	Open document
TSCA	Open document
RoHs	Open document
CMRT	Open document

Further documents

Modbus register S6XM_S9XM	Download document
----------------------------------	-----------------------------------

Software



SensAct-Software	Download software
-------------------------	-----------------------------------

CAD Files

STEP_S9XM_en.stp	Download file
-------------------------	-------------------------------



Media & drawings



Tele Haase Steuergeräte Ges.m.b.H
Vorarlberger Allee 38
1230 Vienna
Austria

CALL US



+43 / 1 / 614 74 - 0

ONLINE SUPPORT



support@tele-haase.at

Changes and errors excepted