
# Eaton 104613

# Catalog Number: 104613

Eaton Moeller series NZM - Molded Case Circuit Breaker. Earthfault release, 300mA, 4p, bottom





Eaton Moeller series NZM release

EAN

4015081044238

**Product Height** 

80 mm

**Product Weight** 

0.9 kg

Certifications

IEC/EN 60947-2

IEC/EN 60947-2 annex B

Catalog Number

104613

Product Length/Depth

180 mm

**Product Width** 

120 mm

Compliances

**IEC** 

RoHS conform



# Product specifications

#### Used with

Four-pole

NZM1-4

N1-4

#### Type

Accessory

Earth-fault releases

#### Special features

Earth-fault release to

IEC/EN 60947-2

not UL/CSA approved

Suitable for use in three-

phase systems

Pulse-current sensitive type

A according to core-balance

principle

For 4 pole NZM1-4 circuit-

breakers and N1-4 switch-

disconnectors

Supply voltage-dependent

Ue = 200 - 415 V 50/60 Hz

Control knobs, sealable.

Bottom mounting up to 100

Α

#### Application

In three-phase systems

### Voltage rating

200 - 415 V AC, min. 80 V AC for detection of fault currents type A/AC (dependent on mains voltage)

#### 10.10 Temperature rise

The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

#### 10.11 Short-circuit rating

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

#### 10.12 Electromagnetic compatibility

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

#### Resources

#### **Brochures**

eaton-digital-nzm-brochure-br013003en-en-us.pdf

eaton-feerum-the-whole-grain-solution-success-story-en-us.pdf

### Catalogs

eaton-digital-nzm-catalog-ca013003en-en-us.pdf

#### Declarations of conformity

DA-DC-03\_NZM1

#### **Drawings**

eaton-circuit-breaker-release-nzm-earth-fault-release-dimensions.eps

 $eaton-circuit-breaker-release-nzm-earth-fault-release-3d-drawing-\\002.eps$ 

eaton-circuit-breaker-symbol-nzm-earth-fault-release-symbol.eps

#### eCAD model

ETN.104613.edz

#### Installation instructions

eaton-residual-current-module-mount-below-nzm1-il01219027z.pdf

#### Installation videos

The new digital NZM Range

Introduction of the new digital circuit breaker NZM

#### mCAD model

DA-CS-nzm1\_4\_xfi

DA-CD-nzm1\_4\_xfi

#### Technical data sheets

eaton-nzm-technical-information-sheet

#### 10.13 Mechanical function

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

#### 10.2.2 Corrosion resistance

Meets the product standard's requirements.

#### 10.2.3.1 Verification of thermal stability of enclosures

Meets the product standard's requirements.

# 10.2.3.2 Verification of resistance of insulating materials to normal heat

Meets the product standard's requirements.

# 10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects

Meets the product standard's requirements.

# 10.2.4 Resistance to ultra-violet (UV) radiation

Meets the product standard's requirements.

#### 10.2.5 Lifting

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.2.6 Mechanical impact

Does not apply, since the entire switchgear needs to be evaluated.

# 10.2.7 Inscriptions

Meets the product standard's requirements.

# 10.3 Degree of protection of assemblies

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.4 Clearances and creepage distances

Meets the product standard's requirements.

#### 10.5 Protection against electric shock

Does not apply, since the entire switchgear needs to be evaluated.

#### 10.6 Incorporation of switching devices and components

Does not apply, since the entire switchgear needs to be evaluated.

# 10.7 Internal electrical circuits and connections

Is the panel builder's responsibility.

### 10.8 Connections for external conductors

Is the panel builder's responsibility.

#### 10.9.2 Power-frequency electric strength

Is the panel builder's responsibility. 10.9.3 Impulse withstand voltage Is the panel builder's responsibility. 10.9.4 Testing of enclosures made of insulating material Is the panel builder's responsibility. Frame NZM1 45 mm Frequency rating 50 Hz / 60 Hz Mounting Method **Bottom** Ambient operating temperature - max 40 °C Ambient operating temperature - min -5 °C Current rating - max 100 A Power on-delay time - max 300 ms Power on-delay time - min 300 ms Rated control supply voltage (Us) at AC, 50 Hz - max 415 V Rated control supply voltage (Us) at AC, 50 Hz - min 200 V Rated control supply voltage (Us) at AC, 60 Hz - max 415 V Rated control supply voltage (Us) at AC, 60 Hz - min 200 V Rated control supply voltage (Us) at DC - max 0 V Current rating - min 15 A Degree of protection IP20 (operating component area) Mounting position

Vertical and 90° in all directions

Lifespan, mechanical

20000 operations

Fault current detection range

50/60 Hz

Number of poles

Four-pole

Terminal capacity (solid/flexible conductor)

As NZM1 standard terminal with ferrules As NZM1 standard terminal without ferrules

Shock resistance

20 g (half-sinusoidal shock 20 ms)

Rated control supply voltage (Us) at DC - min

0 V

Rated fault current - max

0.3 A

Rated fault current - min

0.3 A

Rated operating voltage (Ue) - max

415 V

Sensitivity type

Pulse-current sensitive as per core-balance principle (type A)



Eaton Corporation plc Eaton House 30 Pembroke Road Dublin 4, Ireland Eaton.com

Reserved.

Eaton is a registered trademark.

All other trademarks are © 2024 Eaton. All Rights property of their respective owners.



Eaton.com/socialmedia