

"Universal cross rails, PanelSeT SFN, PanelSeT SF, PanelSeT SM, H40 W1100mm, 1 row, set of 2"

Local distributor code: 398324171

NSYSUCR40110

! Discontinued on: 9 Feb 2023

(!) Discontinued

EAN Code: 3606485133270

Main

Range	PanelSeT
Accessory / separate part category	Mounting accessory
Product or component type	Universal cross rail
Application	Multi-purpose
Nominal dimensions of the	- H: 1100 mm

Complementary

Range compatibility	PanelSeT PanelSeT SF PanelSeT PanelSeT SM PanelSeT PanelSeT SFX PanelSeT PanelSeT SMX	
Mounting location	Between cross rails	
Mounting support	Adaptation profile, on SM enclosures	
Device composition	fixing elements 2 cross rails 4 supports	
Quantity per set	Set of 1	
Material	Steel	
Surface finish	Galvanized	
Fixing mode	By screws	
Adjustment	Adjustable with a pitch of 25 mm	
Number of horizontal rows	1	
Maximum load	30 kg	
Height	Nominal: 1100 mm Useful: 1007 mm	
Width	40 mm	
Depth	27 mm	
Thickness	1.5 mm	

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	5.000 cm

Package 1 Width	6.000 cm
Package 1 Length	102.000 cm
Package 1 Weight	1.998 kg
Unit Type of Package 2	PAM
Number of Units in Package 2	50
Package 2 Height	30.000 cm
Package 2 Width	100.000 cm
Package 2 Length	120.000 cm
Package 2 Weight	113.000 kg

Logistical informations

Country of origin ES

Contractual warranty

Warranty 18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

☑ Environmental footprint	
Carbon footprint (kg.eq.CO2 per CR, Total Life cycle)	14
Environmental Disclosure	Product Environmental Profile

Use Better

S Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
REACh Regulation	REACh Declaration

Use Again

○ Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No