

1328360

https://www.phoenixcontact.com/in/products/1328360

Please be informed that the data shown in this PDF document is generated from our online catalog. Please find the complete data in the user documentation. Our general terms of use for downloads are valid.



Combination of relay interface and electronic fuse protection on overall width: 6.2 mm, individual configuration of the nominal current (1 A ... 6 A), adjustable output characteristic, active signal output, easy system integration, with Push-in connection

## Commercial data

Item number	1328360
Packing unit	1 pc
Minimum order quantity	1 pc
Sales key	CK6
Product key	DK62AF
GTIN	4063151621940
Weight per piece (including packing)	40.2 g
Weight per piece (excluding packing)	40.2 g
Customs tariff number	85364190
Country of origin	DE



1328360

https://www.phoenixcontact.com/in/products/1328360

## Technical data

### Notes

Repeated hard short circuits can reduce the melting integral of the integrated backup fuse.
A suitable flyback diode must be used when switching inductive loads
If the DIP switches are not covered by an adjacent module, the PLC-ATP partition plate must be used for ESD protection
The device contains components that can be damaged or destroyed by electrostatic discharge. When handling the device, observe the necessary safety precautions against electrostatic discharge (ESD) according to EN 61340-5-1 and EN 61340-5-2.
The PLC-ATP separating plate should be installed for safe isolation between adjacent modules
Do not connect adjacent channels to SELV/ PELV and voltages dangerous to the touch.
At least one functional insulation against adjacent modules is complied with in the support rail direction.  If the application has higher requirements on the insulation (basic or reinforced insulation), then these must be realized through suitable measures (e. g., partition plates).
Do not use to separate SELV / PELV circuits from other circuits, because safe isolation is not guaranteed.

## Product properties

Product type	Relay Module
Product family	PLC-INTERFACE
Application	with integrated electronic circuit breaker
Operating mode	100% operating factor

### Insulation characteristics: Air clearances and creepage distances

Insulation	Functional insulation
Overvoltage category	I
Pollution degree	2

## Electrical properties

Maximum power dissipation for nominal condition	< 1.6 W
Fuse	electronic

## Input data

Operating voltage (U <sub>N</sub> )	24 V DC (U <sub>In+</sub> - U <sub>A2</sub> )
Operating voltage range (DC)	19.2 V DC 30 V DC (U <sub>In+</sub> - U <sub>A2</sub> )
Current consumption (In+)	12 mA
Tripping current (I <sub>N</sub> )	1 A (adjustable)
	2 A (adjustable)
	3 A (adjustable)
	4 A (adjustable)



1328360

https://www.phoenixcontact.com/in/products/1328360

	5 A (adjustable)
	6 A (preset)
Measuring tolerance	± 15 %
Power dissipation	0.06 W (Without load, A1 low)
	0.4 W (Without load, A1 high)
	< 1.6 W (Normal operation)
Switching: Switching input A1	
Nominal switch-on voltage	24 V (U <sub>A1</sub> - U <sub>A2</sub> )
Switch-on voltage range	11 V 30 V (U <sub>A1</sub> - U <sub>A2</sub> )
Switch-off voltage range	0 V 2 V (U <sub>A1</sub> - U <sub>A2</sub> )
Current consumption (I <sub>A1</sub> )	4 mA (24 V)
Switch-on time	36 ms
Switch-off time	10 ms
Switching frequency	≤ 2.5 Hz

### Output data

State condition (Error)

State condition (Hiccup mode)

Load circuit: Power MOSFET switching output (positive switching)

<b>.</b>	C,
Voltage drop	0.16 V (6 A, U <sub>In+</sub> - U <sub>out</sub> )
Short-circuit switching capacity	100 A DC
	300 A DC (<5 short circuits)
Required backup fuse	Only required if I <sub>max</sub> of power supply unit > short-circuit switching capacity. Integrated failsafe element
Fail-safe element	15 A
Surge voltage protection	> 33 V
Max. capacitive load	12000 μF (Depending on the current setting and the short-circuit current available)
Shutdown time ()	≤ 15 ms (Short circuit ≥3 x I <sub>N</sub> )
	0.1 s (Short circuit 2 <3 x I <sub>N</sub> )
	1 s (Short circuit 1.5 <2 x I <sub>N</sub> )
	4 s (Short circuit 1.1 <1.5 x I <sub>N</sub> )
Undervoltage switch-off	≤ 17.8 V (active)
	≥ 19 V (inactive)
Overvoltage switch-off	≥ 30.5 V (active)
	≤ 29.5 V (inactive)
Waiting time	5 s (Between the pulses)
Number	5 (Start attempts in hiccup mode)
gnal: Feedback contact	
Output voltage	U <sub>In+</sub> - 0.7 V (high level)
Current (Maximum current)	≤ 20 mA
State condition (Normal operation)	low

high (Fuse has blown)

high (After all 5 start attempts have been completed)



1328360

https://www.phoenixcontact.com/in/products/1328360

### Connection data

Connection method	Push-in connection
Stripping length	8 mm
Conductor cross section rigid	0.14 mm² 1.5 mm²
Conductor cross section flexible	0.14 mm² 1.5 mm²
Conductor cross section flexible (2 conductors with same cross section)	0.5 mm <sup>2</sup> 1.5 mm <sup>2</sup> (TWIN ferrule with plastic sleeve)
Conductor cross section AWG	26 14

### **Dimensions**

### Item dimensions

Width	6.2 mm
Height	80 mm
Depth	94 mm

### Environmental and real-life conditions

### Ambient conditions

Degree of protection	IP20
Degree of protection (Installation location)	≥ IP54
Ambient temperature (operation)	-25 °C 55 °C (Observe derating in the connected state)
Ambient temperature (storage/transport)	-40 °C 70 °C
Altitude	≤ 2000 m (Without derating)
	≤ 3000 m (With correction factor for ambient temperature (operation) x 0.88)
Permissible humidity (operation)	95 %

## Approvals

### UL, USA/Canada

2, 00, 00, 100, 100	
Identification	UL 2367
	UL 60947-1
	UL 60947-5-1
	CSA C22.2 No. 60947-1
	CSA C22.2 No. 60947-5-1
UL data	
Operating mode	Indoor use

## Standards and regulations

### Electromagnetic compatibility (EMC)

Standards/regulations	EN 61000-6-2
	EN 61000-6-3

### Air clearances and creepage distances



1328360

https://www.phoenixcontact.com/in/products/1328360

	Standards/regulations	IEC 60664			
Мс	Mounting				
	Mounting type	DIN rail mounting			
	Assembly note	in rows with zero spacing			
	Mounting position	any			



1328360

https://www.phoenixcontact.com/in/products/1328360

## **Approvals**

To download certificates, visit the product detail page: https://www.phoenixcontact.com/in/products/1328360



**UL Recognized**Approval ID: E317172



**cULus Listed** Approval ID: E140324



1328360

https://www.phoenixcontact.com/in/products/1328360

## Classifications

### **ECLASS**

ECLASS-11.0	27140401
ECLASS-12.0	27140401
ECLASS-13.0	27140401

## **ETIM**

ETIM	9.0	EC003538



1328360

https://www.phoenixcontact.com/in/products/1328360

## Environmental product compliance

### EU RoHS

Fulfills EU RoHS substance requirements	Yes
Exemption	7(a), 7(c)-l
China RoHS	
Environment friendly use period (EFUP)	EFUP-50
	An article-related China RoHS declaration table can be found in the download area for the respective article under "Manufacturer declaration". For all articles with EFUP-E, no China RoHS declaration table issued and required.
EU REACH SVHC	
REACH candidate substance (CAS No.)	Lead(CAS: 7439-92-1)



1328360

https://www.phoenixcontact.com/in/products/1328360

### Accessories

### FBST 500-PLC RD - Continuous plug-in bridge

2966786

https://www.phoenixcontact.com/in/products/2966786



Continuous plug-in bridge, length: 500 mm, color: red

## FBST 500-PLC BU - Continuous plug-in bridge

2966692

https://www.phoenixcontact.com/in/products/2966692



Continuous plug-in bridge, length: 500 mm, color: blue



1328360

https://www.phoenixcontact.com/in/products/1328360

## FBST 6-PLC RD - Single plug-in bridge

2966236

https://www.phoenixcontact.com/in/products/2966236



Single plug-in bridge, number of positions: 2, length: 6 mm, color: red

### FBST 6-PLC BU - Single plug-in bridge

2966812

https://www.phoenixcontact.com/in/products/2966812

Single plug-in bridge, number of positions: 2, length: 6 mm, color: blue





1328360

https://www.phoenixcontact.com/in/products/1328360

### PLC-V8/FLK14/OUT - System connection

#### 2295554

https://www.phoenixcontact.com/in/products/2295554



V8 adapter for 8 x PLC-INTERFACE (6.2 mm), controller: PLC system cabling of output cards, connection 1: IDC/FLK pin strip 1x 14-position, connection 2: Plugin connection (Can be snapped onto 8x PLC-INTERFACE terminals), connection 3: Screw connection 1x 2-position, number of channels: 8, control logic: positive switching

### PLC-V8/D15S/OUT - System connection

### 2296058

https://www.phoenixcontact.com/in/products/2296058



V8 adapter for 8 x PLC-INTERFACE (6.2 mm), controller: PLC system cabling of output cards, connection 1: D-SUB pin strip 1x 15-position, connection 2: Plug-in connection (Can be snapped onto 8x PLC-INTERFACE terminals), connection 3: Screw connection 1x 2-position, number of channels: 8, control logic: positive switching



1328360

https://www.phoenixcontact.com/in/products/1328360

### PLC-ESK GY - Power terminal block

2966508

https://www.phoenixcontact.com/in/products/2966508



Power terminal block, for the input of up to four potentials, for mounting on NS 35/7.5

### PLC-ATP BK - Separating plate

2966841

https://www.phoenixcontact.com/in/products/2966841



Separating plate, 2 mm thick, required at the start and end of a PLC terminal strip. Furthermore, it is used for: visual separation of groups, safe isolation of different voltages of neighboring PLC relays in acc. with DIN VDE 0106-101, isolation



1328360

https://www.phoenixcontact.com/in/products/1328360

REL-MR- 24DC/21 - Single relay

2961105

https://www.phoenixcontact.com/in/products/2961105



Plug-in miniature power relay, with power contact, 1 changeover contact, input voltage 24 V DC

Phoenix Contact 2025 @ - all rights reserved https://www.phoenixcontact.com

PHOENIX CONTACT (I) Pvt. Ltd. A-58/2, Okhla Industrial Area, Phase - II, New Delhi-110 020

+91.1275.71420 info@phoenixcontact.co.in