

Talento 892 Plus & Talento CE Plus



TALENTO 892+



TALENTO CE+

		Grässlin	
		Digital annual	Accessories
Product Name		talento 892 plus	talento CE plus
Total Channels Expanded		Expandable to 8 channels	
Channels		2	2
Switch contacts		changeover contacts	changeover contacts
Communication		Powerline Protocol GPL	Powerline Protocol GPL
No. of Modules		3	2
Connection voltage	230V AC/50-60Hz	multivoltage (230/120)	multivoltage (230/120)
	120 VAC/60Hz	multivoltage (230/120)	multivoltage (230/120)
	24V AC/DC	X	X
	12 V DC	--	--
AC Switching capacity	12 VAC/50Hz	--	--
	ohmic load (VDE,IEC)	16 A / 250 V AC	16 A / 250 V AC
	inductive load cos. 0.6	10 A / 250 V AC	8 A / 250 V AC
	incandescent lamp load	2600 W	1000 W
Memory spaces		800	--
Programs	ON/OFF	X	X*
	Pulse function	X	X*
	Cycle function	X	X*
	Random switching	X	X*
	Impulse counter	X	X*
	Hour counter	X	X*
	Holiday programming	X	X*
	Free weekday block formation	X	X*
	Date-dependent switching program	X	X*
DCF/GPS		--	--
Manual switch		Fix ON/OFF OVERRIDE	Fix ON/OFF OVERRIDE
PC programming and monitoring	Data transfer device	Hand-held programming device talento taxxi plus	X*
	LAN	X	X**
	Internet	X	X**
Running reserve		3 years replaceable	--
Accuracy		typ +/- 0,3 s/day at + 20°C	--
Display lighting		X	--
Language of menu technology		D,GB,F,I,E,P,CZ,NL,S,N,DK,FIN,PL,H	no menu technology

*) in combination with talento 992 plus

**) in combination with talento LAN plus