

Datasheet

RS Pro Straight 50Ω RF Adapter BNC Socket to BNC Socket

RS Stock No: **546-4572**



Product Details

RS Pro RF adapter has BNC socket connector on both the ends that comes with an impedance of 50 Ω. The RF adapter has straight body orientation and is made of copper material.

Features and Benefits

- Nominal impedance of 50Ω
- Copper contacts
- Straight orientation

Specifications:

| | |
|-----------------------|--------------------------|
| Adapter Type A | BNC |
| Adapter Type B | BNC |
| Adapter Type | BNC Socket to BNC Socket |
| Body Orientation | Straight |
| Body Plating | Silver |
| Contact Material | Copper |
| Contact Plating | Silver |
| Gender A | Socket |
| Gender B | Socket |
| Impedance | 50 Ω |
| Length | 32.5 mm |
| Operating Frequency | 0 to 4 GHz |
| Body Material | Brass |
| Insulation Material | PTFE |
| Operating Temperature | -65 to +165°C |
| Voltage Rating | 500 V |
| | |