Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

white light block with body/fixing collar with integral LED 12...24V



Local distributor code: 398151739 ZB6EB1A

EAN Code: 3389110784237

Main

Range of product	Harmony XB6	
Product or component type	Complete body for pilot lights	
Device short name	ZB6	
Sale per indivisible quantity	5	
Connections - terminals	Pins for printed circuit board, connection size: 1 x 0.5 mm	
Light source	LED	
Bulb base	Integral LED	
Light block supply	Direct	
Light source colour	White	
[Us] rated supply voltage	12 24 V AC/DC	

Complementary

CAD overall height	16 mm	
CAD overall depth	58 mm	
Terminals description ISO n°1	(X1-X2)PL	
Net weight	0.003 kg	
Operating position	Any position	
[Ui] rated insulation voltage	250 V (pollution degree 3) conforming to IEC 60947-1	
[Uimp] rated impulse withstand voltage	4 kV conforming to IEC 60947-1	
Signalling type	Steady	
Supply voltage limits	630 V AC/DC	
Current consumption	15 mA	
Surge withstand	1 kV in contact conforming to IEC 61000-4-5 2 kV in free air conforming to IEC 61000-4-5	

Environment

Protective treatment	TC
Ambient air temperature for storage	-4070 °C
Ambient air temperature for operation	-2570 °C
Electrical shock protection class	Class II conforming to IEC 61140

Standards	JIS C 4520 IEC 60947-5-1 CSA C22.2 No 14 IEC 60947-1 JIS C 852 IEC 60947-5-5 UL 508	
Product certifications	CSA GOST CCC UL	
Vibration resistance	+/- 3 mm (f= 2500 Hz) conforming to IEC 60068-2-6 5 gn (f= 2500 Hz) conforming to IEC 60068-2-6	
Shock resistance	30 gn (duration = 18 ms) for half sine wave acceleration conforming to IEC 60068-2-27 50 gn (duration = 11 ms) for half sine wave acceleration conforming to IEC 60068-2-27	
Resistance to fast transients	2 kV conforming to IEC 61000-4-4	
Resistance to electromagnetic fields	10 V/m conforming to IEC 61000-4-3	
Resistance to electrostatic discharge	6 kV on contact (on metal parts) conforming to IEC 61000-2-6 8 kV in free air (in insulating parts) conforming to IEC 61000-2-6	
Electromagnetic emission	Class B conforming to IEC 55011	

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	8.0 cm
Package 1 Width	2.1 cm
Package 1 Length	6.4 cm
Package 1 Weight	4.0 g
Unit Type of Package 2	CAR
Number of Units in Package 2	5
Package 2 Height	8.0 cm
Package 2 Width	2.1 cm
Package 2 Length	6.4 cm
Package 2 Weight	22.0 g

Logistical informations

Country of origin FR

Contractual warranty

Warranty 18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

Use Better

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	Yes
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
SCIP Number	7e93e493-8304-40e7-9b39-3ac9fc039df4

Use Again

○ Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No


Product datasheet

ZB6EB1A

Dimensions Drawings

Body for Pilot Light

Dimensions




b 15.5 mm/0.61 in.

ZB6EB1A


Mounting and Clearance

Pushbuttons, Switches and Pilot Lights for Printed Circuit Board Connection

Front Panel Cut-out (Viewed from Installer's Side)



Printed Circuit Board Drillings (Viewed from Electrical Block Side)



 ${\bf A}$ 24 mm/0.94 in. minimum for rectangular heads, 18 mm/0.71 in. minimum for square or circular heads ${\bf B}$ 18 mm/0.71 in. minimum

(1) 6 x Ø 1.1 mm / 6 x Ø 0.04 in. holes.

(2) 1 x \varnothing 2.6 $^{0}_{-0.2}$ mm / 1 x \varnothing 0.10 $^{0}_{-0.008}$ in. hole for locating pin, only when using socket adaptor ZB6Y010.

(3) 1 x \varnothing 3.2 $^{0}_{-0.2}$ mm / 1 x \varnothing 0.13 $^{0}_{-0.008}$ in. hole for fixing of printed circuit board onto the front panel using body

bracket ZB6Y011. This hole must be drilled on the left-hand side, when heads are positioned at the normal angle. Fit a body bracket ZB6Y011 every 72 mm/2.83 in. maximum for cut-outs on 24 mm/0.94 in. centres (rectangular heads) and 54 mm/2.13 in. maximum for cut-outs on 18 mm/0.71 in. centres (square or circular heads).


General tolerances of the panel and printed circuit board: T1, T2: T1 + T2 = 0.3 mm/0.01 in. maximum. Installation precautions:

Thickness of printed circuit board: 1.6 mm/0.06 in. minimum.

Mounting with Body Bracket


ZB6EB1A

With socket adaptor ZB6Y010



- (1) Head
- (2) Nut
- (3) Body
- (4) Body bracket
- (5) Contact block
- (6) Socket adaptor
- (7) Panel
- (8) Printed circuit

Direct mounting without socket adaptor ZB6Y010



- (1) Head
- (2) Nut
- (3) Body
- (4) Body bracket
- (5) Contact block
- (6) Panel
- (7) Printed circuit