SIEMENS

Product data sheet 3RT1036-1AK60



CONTACTOR, AC-3 22 KW/400 V, AC 110V 50HZ/120V 60HZ 3-POLE, SIZE S2, SCREW CONNECTION

General technical data:			
product brand name		SIRIUS	
Size of the contactor		S2	
Protection class IP / on the front		IP20	
Degree of pollution		3	
Installation altitude / at a height over sea level / maximum	m	2,000	
Ambient temperature / during operating	°C	-25 +60	
Mechanical operating cycles as operating time			
of the contactor / typical		10,000,000	
• of the contactor with added auxiliary switch block / typical		10,000,000	
 of the contactor with added electronics-compatible auxiliary switch block / typical 		5,000,000	

Main circuit:			
Number of NC contacts / for main contacts		0	
Number of NO contacts / for main contacts		3	
Operating current			
• at AC-1 / at 400 V			
• at 40 °C ambient temperature / rated value	А	60	
• at 60 °C ambient temperature / rated value	А	55	
• at AC-3 / at 400 V / rated value	Α	50	

• at AC-4 / at 400 V / rated value	Α	41
• with 1 current path / at DC-1		
• at 24 V / rated value	Α	55
• at 110 V / rated value	Α	4.5
 with 2 current paths in series / at DC-1 		
• at 24 V / rated value	Α	55
• at 110 V / rated value	Α	25
 with 3 current paths in series / at DC-1 		
• at 24 V / rated value	Α	55
• at 110 V / rated value	Α	55
with 1 current path / at DC-3 / at DC-5		
• at 24 V / rated value	Α	35
• at 110 V / rated value	Α	2.5
 with 2 current paths in series / at DC-3 / at DC-5 		
• at 24 V / rated value	Α	55
• at 110 V / rated value	Α	25
 with 3 current paths in series / at DC-3 / at DC-5 		
• at 24 V / rated value	Α	55
• at 110 V / rated value	Α	55
Service power		
• at AC-2 / at 400 V / rated value	kW	22
• at AC-3 / at 400 V / rated value	kW	22
at AC-4 / at 400 V / rated value	W	22,000
Active power loss / per conductor / typical	W	5

Control circuit:		
Type of voltage / of the controlled supply voltage		AC
Control supply voltage / 1		
• at 50 Hz / for AC		
• rated value	V	110
• at 60 Hz / for AC		
• rated value	V	120
Operating range factor control supply voltage rated value / of the magnet coil		
• at 50 Hz		
• for AC		0.8 1.1
• at 60 Hz		
• for AC		0.8 1.1
Apparent pull-in power / of the solenoid / for AC	V-A	166
Apparent holding power / of the solenoid / for AC	V-A	12.6

Inductive power factor / with the pull-in power of the coil	0.71	
Inductive power factor / with the pull-in power of the coil	0.37	

Auxiliary circuit:		
Contact reliability / of the auxiliary contacts		1 faulty switching per 100 million (17 V, 1 mA)
Number of NC contacts / for auxiliary contacts / instantaneous switching		0
Number of NO contacts / for auxiliary contacts / instantaneous switching		0
Operating current / of the auxiliary contacts		
• at AC-12 / maximum	Α	10
• at AC-15		
• at 230 V	Α	6
• at 400 V	Α	3
• at DC-12		
• at 60 V	Α	6
• at 110 V	Α	3
• at 220 V	Α	1
• at DC-13		
• at 24 V	Α	10
• at 60 V	Α	2
• at 110 V	Α	1
• at 220 V	Α	0.3

Short-circuit:	
Design of the fuse link	
• for short-circuit protection of the auxiliary switch / required	fuse gL/gG: 10 A
• for short-circuit protection of the main circuit	
• with type of assignment 1 / required	fuse gL/gG: 160 A
• at type of coordination 2 / required	fuse gL/gG: 80 A

Installation/mounting/dimensions:			
Type of mounting		screw and snap-on mounting onto 35 mm standard mounting rail according to DIN EN 50022	
series installation		Yes	
Width	mm	55	
Height	mm	112	
Depth	mm	115	
Distance, to be maintained, to earthed part / sidewards	mm	6	

Connection type:	
Design of the electrical connection	

- for main current circuit
- for auxiliary and control current circuit

screw-type terminals

screw-type terminals

Certificates/approvals:

General Product Approval

Functional Safety / Safety of Machinery Declaration of Conformity









Type Examination



Test Certificates

Special Test Certificate Type Test
Certificates/Test
Report

Shipping Approval













Shipping Approval

other



Confirmation

other

Environmental Confirmations

Further information:

Information- and Downloadcenter (Catalogs, Brochures,...)

http://www.siemens.com/industrial-controls/catalogs

Industry Mall (Online ordering system)

http://www.siemens.com/industrial-controls/mall

Cax online generator:


http://www.siemens.com/cax

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

 $\underline{\text{http://support.automation.siemens.com/WW/view/en/3RT1036-1AK60/all}}$

 ${\bf Image\ database\ (product\ images,\ 2D\ dimension\ drawings,\ 3D\ models,\ device\ circuit\ diagrams,\ ...)}$

 $\underline{\text{http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3RT1036-1AK60}}$



last change:

Jun 28, 2012