

Datasheet

RS Pro Straight 50Ω Coaxial Adapter BNC Female to BNC Female 0 to 4GHz

RS Stock No: **546-4083**



Product Details

RS Pro coaxial adapter has BNC female connector on both the ends that works at a operating frequency of 0 to 4 GHz. This adapter is suitable for a variety of applications including video signalling and test equipment. The straight adapter has a impedance of 50 Ω.

Features and Benefits

- Ideal for video signalling and test equipment.
- Frequency of 0 to 4 GHz
- Gold plated body

Specifications:

Adapter Type A	BNC
Adapter Type B	BNC
Adapter Type	BNC Socket to BNC Socket
Body Orientation	Straight
Body Plating	Nickel
Contact Material	Brass
Contact Plating	Gold
Gender A	Female
Gender B	Female
Impedance	50 Ω
Length	32.5 mm
Operating Frequency	0 to 4 GHz
Polarity	Normal
Body Material	Brass
Insulation Material	PTFE
Operating Temperature	-65 to +165°C
Voltage Rating	500 V