

RCD Protection

RCD05WAV Valiance RCD Twin White - Active

Twin socket RCD circuit breaker simply replaces an existing twin socket providing two protected switched socket outlets. The contacts break when power supply is temporarily lost.

- Provides two protected switched socket outlets for convenience and extra safety.
- Protects appliances from possible fire hazard.
- Manual reset.
- Extra fast action – trips out within 40 milliseconds (BS7288).
- Automatically disconnects both Live and Neutral connections leaving Earth connection intact.
- Trips out when the power supply is temporarily lost. A safety must for machine tool applications.
- Test button for safety checks.
- Still protects with lost neutral.
- Still protects with pulsating DC earth fault currents.
- Complies with BS7288 and BS1363.
- **Part No. RCD05WAV**



Specification

Type	Active – Non-Latching
Operating Voltage	230V AC
Current Rating	Fully complies with BS1363
Rated Trip Current	30mA
Trip Speed	BS 7288 – 40ms
Contact Break	Double Pole
Continues to Protect With	Lost Neutral & Pulsating DC Earth Fault
Cable Capacity	Up to 10.5mm ²
Conforms To	BS1363, BS7288
Dimensions (mm)	Height 86, Width 147, Depth 42.5
Minimum Box Depth	25mm