


Product datasheet

Specifications



Front Connection Cover MTZ2/NW PrismaSet P

LVS04861

EAN Code: 3606481880222

Main

Range	PrismaSeT
Range of product	PrismaSeT P
Product or component type	Front connection cover
Accessory / separate part category	Interface accessory
Range compatibility	PrismaSeT PrismaSeT P framework
Cubicle partitioning form	Form 1

Complementary

installation description	Cubicle
Installed device	fixed + drawout NW08...32 fixed + drawout NW40
Quantity per set	Set of 1
Net weight	9.26 kg
Surface finish	Matt Textured
Protective treatment	Electrophoresis treatment and hot-polymerised polyester epoxy powder
Colour	White (RAL 9003)

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	9.500 cm
Package 1 Width	63.000 cm
Package 1 Length	70.500 cm
Package 1 Weight	9.844 kg
Unit Type of Package 2	P12
Number of Units in Package 2	20
Package 2 Height	98.000 cm
Package 2 Width	80.000 cm
Package 2 Length	120.000 cm
Package 2 Weight	208.900 kg

Logistical informations

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Country of origin	FR
-------------------	----

Contractual warranty

Warranty	18 months
----------	-----------

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint	
Environmental Disclosure	Product Environmental Profile

Use Better

Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
REACH Regulation	REACH Declaration
PVC free	Yes

Use Again

Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No

Technical Illustration

Dimensions

