



ITEM. 05545

SIP STARTMASTER PWT5500 STARTER CHARGER

HIGH-QUALITY BENCH DRILLING FOR HOME USERS & ENTHUSIASTS



PRODUCT DESCRIPTION

The **SIP STARTMASTER PWT5500 Starter Charger** is an intelligent charger built with safe and automatic boost starting, along with 4 versatile charging levels and timer, and offers full compatibility with all Lead Acid, SLA, AGM, GEL, WET and VRLA batteries.

KEY FEATURES

- ✓ 12v/24v charging voltage and 300A max. boost rate
- ✓ Intelligent charging with battery type selection
- 4 versatile charging levels and charging timer
- Automatic battery maintainer on all batteries
- Clear and easy-to-read control panel

ITEM. 05545

SIP STARTMASTER PWT5500 STARTER CHARGER

ADDED FEATURES

- ✓ 12v/24v charging voltage and 300A max. boost rate
- 450Ah max. battery capacity and 30A charging current
- 4 different charge rate settings for added versatility
- Easy battery type selection for Lead Acid, SLA, AGM, GEL, WET, and VRLA
- ✓ Integrated charging timer and automatic battery maintainer on all types
- Safe Start function helps protect vehicle electronics
- Auto Boost Start offers one-man operation
- Wheel-mounted steel casing for increased mobility
- Remote lead for easy one-man operation
- Heavy-duty leads and crocodile clips
- Manufactured in Italy

APPLICATIONS & USES

Perfect for professional-grade workshops and garages.

TECHNICAL INFORMATION

ITEM NO.	05545
Input Supply:	230v (16A)
Output Voltages:	12v / 24v
Battery Capacity:	450Ah
Average Current Output:	30A (12v) / 15A (24v)
Max. Current Output:	45A (12v) / 22.5A (24v)
Max. Boost Current:	Fully discharged 300A / Medium discharged 200A
Internal Fuse Rating:	120A
Charge Rate Settings:	4 settings / boost
Compatible Battery Types:	PB, SLA, AGM, GEL, WET, VRLA
Net Weight:	17.60kg
Gross Weight:	19.30kg
Product Dimensions:	720(H) x 440(W) x 320mm(D)
Packaged Dimensions:	360(H) x 400(W) x 700mm(D)

