LG8K06Q706

Main

Enclosed reversing starter, TeSys LG,1-1.6A,380/400V AC coil, including 2 LC1K,GV2ME, pushbutton, 2-pos switch

Range	TeSys
Product name	TeSys LG
Device short name	LG8K
Product or component type	Enclosed DOL reversing starter
Device application	Safety
Utilisation category	AC-3
Device composition	Reversing contactor Circuit-breaker
Motor power kW	0.25 KW at 220/230 V AC 50/60 Hz 0.55 KW at 400/415 V AC 50/60 Hz 0.55 kW at 440 V AC 50/60 Hz

[Uc] control circuit voltage	380/400 V AC 50/60 Hz
Control type	Push-button stop black O Selector switch 2 positions start black I-II Mushroom head push-button emergency stop red

1...1.6 A

Complementary

Width	175 mm	
Height	165 mm	
Depth	146 mm	
Net weight	1.64 kg	
Cable entry number	4 2 Pg 13 + 2 Pg 16 top 4 2 Pg 13 + 2 Pg 16 bottom	

Thermal protection

adjustment range

Environment

IEC 60204-1	
IEC 60947-4-1	
CE[RETURN]UKCA	
IP55 conforming to IEC 60529 (for enclosure)	
IK07 conforming to IEC 60529	
Polycarbonate	
Standard environment	
	CE[RETURN]UKCA IP55 conforming to IEC 60529 (for enclosure) IK07 conforming to IEC 60529 Polycarbonate

Offer Sustainability

REACh Regulation	REACh Declaration
EU RoHS Directive	Compliant with Exemptions
Mercury free	Yes
RoHS exemption information	₽¥Yes
China RoHS Regulation	China RoHS Declaration
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins