# Disclaimer. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



# PILOT LIGHT 120VAC 30MM TYPE K +OPTIONS

9001KP1W31

EAN Code: 3389118041387

### Main

Range of product	Harmony 9001K	
Product or component type	Pilot light	
Device short name	K	

# Complementary

Bezel material	Metal	
Mounting diameter	30 mm	
Lens type	Fresnel plastic	
Cap/operator or lens colour	White	
Light source	incandescent	
Bulb base	BA 9s	
Light block supply	Via transformer 120 V AC 50/60 Hz Via integral transformer 110 V AC 50/60 Hz	
Connections - terminals	Screw clamp terminals, 1 x 0.222 x 1.5 mm² conforming to IEC 60947-1	
Shape of screw head	Round	
Operating position	Any position	
Light source	Incandescent bulb	
[Us] rated supply voltage	110120 V AC	
Operating mode	Normal	
Device presentation	Complete product	
Lens type	Fresnel	
[Us] rated supply voltage	110120 V	
Light block supply	Via integral transformer	
Supply frequency	5060 Hz	
Lens material	Polycarbonate	
Size	30 mm	

### **Environment**

Product certifications	CSA LR25490 class 3211 03 CE UL listed file E42259 CCN NKCR
NEMA degree of protection	NEMA 1/2/3/3R/4/6/12/13

# **Packing Units**

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	5.588 cm
Package 1 Width	9.398 cm
Package 1 Length	4.572 cm
Package 1 Weight	222.26 g

# **Contractual warranty**

Warranty 18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

### **Use Better**

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	Yes
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
SCIP Number	Ae0c4eb9-0bfb-40a4-851f-5c619fbe777d
REACh Regulation	REACh Declaration

### **Use Again**

○ Repack and remanufacture	
Take-back	No
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins