

"One entry cable gland plate, PanelSeT SFN, PanelSet SF, for electrical enclosure W400 D800mm, fixed by clips"

Local distributor code: 398247148

NSYEC481

EAN Code: 3606485126234

Main

Range	PanelSeT	
Product or component type	Cable gland plate	
Accessory / separate part category	Cable management accessory	
Application	Multi-purpose	
Range compatibility	PanelSeT PanelSeT SF PanelSeT PanelSeT SFM	
Mounting location	Enclosure bottom	
Cable gland type	Standard	
Cable entry	1 entry	
Device composition	fixing elements 1 plate self extinguishing polyurethane adhesive gasket with cross-section of 15 x 25 mm	
Quantity per set	Set of 1	
Material	Galvanised steel	

Complementary

Height	35 mm	
Width	Nominal: 400 mm Useful: 216 mm Real: 175 mm	
Depth	Nominal : 800 mm	
Thickness	1.5 mm	

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	3.500 cm
Package 1 Width	17.500 cm
Package 1 Length	65.500 cm
Package 1 Weight	2.740 kg
Unit Type of Package 2	PAL
Number of Units in Package 2	10
Package 2 Height	29.000 cm

Package 2 Width	37.500 cm
Package 2 Length	120.000 cm
Package 2 Weight	27 400 kg

Logistical informations

Country of origin

Contractual warranty

Coverage	Core product
Warranty	18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

⊘ Environmental footprint	
Carbon footprint (kg.eq.CO2 per CR, Total Life cycle)	19
Environmental Disclosure	Product Environmental Profile

Use Better

Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
SCIP Number	52da316e-d4e1-4114-85c0-32a03b2934fd
REACh Regulation	REACh Declaration

Use Again

○ Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No