

# Product datasheet

Specifications



## Mureva FIX - instaclip for Ø25 mm conduits

ENN45025

### Main

range of product	Mureva
Product or component type	Conduit support
colour	Grey (RAL 7035)
quantity per package	100 pieces

### Complementary

Accessory / separate part category	Installation accessory
Condition of use	Indoor
Tube diameter	25 mm
Material	PA (polyamide) 6/6
Fixing mode	By Murafix plug By screw
Net weight	0.002 kg

### Environment

operating temperature	-5...60 °C
-----------------------	------------

### Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	8.000 cm
Package 1 Width	12.500 cm
Package 1 Length	0.190 cm
Package 1 Weight	2.000 g
Unit Type of Package 2	CAR
Number of Units in Package 2	1000
Package 2 Height	30.500 cm
Package 2 Width	40.500 cm
Package 2 Length	20.500 cm
Package 2 Weight	2.876 kg
Unit Type of Package 3	P12
Number of Units in Package 3	40000

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Package 3 Height	117.500 cm
Package 3 Width	80.000 cm
Package 3 Length	120.000 cm
Package 3 Weight	128.000 kg

## Contractual warranty

Warranty	18 months
----------	-----------



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint	
Carbon footprint (kg.eq.CO2 per CR, Total Life cycle)	1
Environmental Disclosure	<a href="#">Product Environmental Profile</a>

### Use Better

Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
<a href="#">EU RoHS Directive</a>	Pro-active compliance (Product out of EU RoHS legal scope)
REACH Regulation	<a href="#">REACH Declaration</a>

### Use Again

Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No