

"Quick fixing cross rails, PanelSeT SFN, PanelSeT SF, PanelSeT SM, H40 W400mm, 1 row, set of 2"

Local distributor code: 385515430 NSYSQCR4040

EAN Code: 3606485132648

Main

Range	PanelSeT
Accessory / separate part category	Mounting accessory
Product or component type	Quick cross rails
Application	Multi-purpose
Nominal dimensions of the housing	-

Complementary

Range compatibility	PanelSeT PanelSeT SF PanelSeT PanelSeT SM PanelSeT PanelSeT SFX PanelSeT PanelSeT SMX	
Mounting location	On structure of enclosure Between cross rails	
Mounting support	Adaptation profile, on SM enclosures	
Device composition	fixing elements 2 cross rails	
Quantity per set	Set of 1	
Material	Steel	
Surface finish	Galvanized	
Fixing mode	By screws Clipped - on structure location	
Adjustment	Adjustable with a pitch of 25 mm	
Number of horizontal rows	1	
Maximum load	60 kg	
Height	Nominal: 400 mm Useful: 310 mm	
Width	40 mm	
Depth	27 mm	
Thickness	1.5 mm	

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	5.000 cm
Package 1 Width	6.500 cm

Package 1 Length	38.000 cm
Package 1 Weight	626.000 g
Unit Type of Package 2	PAM
Number of Units in Package 2	550
Package 2 Height	105.000 cm
Package 2 Width	100.000 cm
Package 2 Length	120.000 cm
Package 2 Weight	365.000 kg

Logistical informations

Country of origin

Contractual warranty

Coverage	Core product
Warranty	18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

∇ Environmental footprint	
Carbon footprint (kg.eq.CO2 per CR, Total Life cycle)	5
Environmental Disclosure	Product Environmental Profile

Use Better

Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
REACh Regulation	REACh Declaration

Use Again

○ Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No