



English

## Product Datasheet

Stock No: 193-8694

# 3 in 1 Stud/Metal/AC Voltage Finder

EN



## Introduction

The Stud Tester uses electronic signals to locate the edges of studs, joists or live AC wires through drywall or other common building materials. Range selected by activation button for 1/2 inch, 1 inch and 1½ inch. Once the edge of a metal or wooden beam has been detected the two stud detection LED of Stud Tester illuminate and sounds an audible tone.

## Specification

Wood or Metal Studs	0 ~ 1½"(38mm) through drywall
Live AC Wires (110vAC)	0 ~ 2"(50mm) through drywall
Operating Temperature	0°C to 50°C (32°F to 122°F)
Storage Temperature	-10°C to 60°C (14°F to 140°F)
Power Source	9V

Accessories:

9V battery and Gift box.